भारतीय रेल Indian Railways

पटियाला रेलइंजन कारख़ाना, पटियाला

PATIALA LOCOMOTIVE WORKS, PATIALA



LOCO TESTING & DISPATCH REPORT OF IGBT BASED wAg9hc ELECTRIC LOCOMOTIVE

LOCO NO.: 42043

TYPE: WAG9HC

Rail way shed: ner/syhe

ProPulsion system: bhel

Date of Dispatch: 30.06.2025

लोको निर्माण रिकार्ड



पटियाला रेलइंजन कारख़ाना, पटियाला PATIALA LOCOMOTIVE WORKS, PATIALA

LOCO NO.: 42043

RAILWAY/SHED: NER/SYHE

DOD: June-2025

INDEX

SN	PARA	ACTIVITIES	PAGE NO.		
	Testing & Commissioning (ECS)				
1.	1.0	Continuity Test of the cables			
	1.1	Continuity Test of Traction Circuit Cables			
	1.2	Continuity Test of Auxiliary Circuit Cables	1-4		
	1.3	Continuity Test of Battery Circuit Cables			
	1.4	Continuity Test of Screened Control Circuit Cables			
2.	2.0	Low Tension test			
	2.1	Measurement of resistor in OHMS (Ω)	5-6		
	2.2	Check Points	3-0		
	2.3	Low Tension Test Battery Circuits (without control electronics)			
3	3.0	Downloading of Software			
	3.1	Check Points			
	3.2	Download Software	7-10		
	3.3	Analogue Signal Checking			
	3.4	Functional test in simulation mode			
4	4.0	Sensor test & convertor test			
	4.1	Test wiring Transformer Circuits – Polarity Test			
	4.2	Test wiring auxiliary transformer 1000V/415V-110V (pos. 67)			
	4.3	Primary Voltage Transformer			
	4.4	Minimum voltage relay (Pos. 86)	11-16		
	4.5	Maximum current relay (Pos. 78)	17.76		
	4.6	Test current sensors			
	4.7	Test DC Link Voltage Sensors (Pos 15.6/*)			
	4.8	Verification of Converter Protection Circuits (Hardware limits)			
	4.9	Sequence of BUR contactors			
5.	5.0	Commissioning with High Voltage			
	5.1	Check List			
	5.2	Safety test main circuit breaker			
	5.3	Auxiliary Converter Commissioning			
	5.3.1	Running test of 3 ph. auxiliary equipments			
	5.3.2	Performance of Auxiliary Converters	40.05		
	5.3.3	Performance of BURs when one BUR goes out	16-25		
	5.4 5.5	Auxiliary circuit 415/110			
	5.5 5.6	Hotel Load Circuit Treation Convertor Commissioning			
	5.6 5.7	Traction Converter Commissioning Test protective shutdown SP			
	5.7 5.8	Test protective shutdown SR Test Harmonic Filter			
	5.6 5.9	Test important components of the locomotive			
6.	6.0	Running Trial of the locomotive	25-26		
7.	7.0	Final Check List to be verified at the time of Loco dispatch	27		
8.	8.0	Status of RDSO modifications	28		
9.	1-10	Pneumatic Test Parameters	29 - 32		
10.		Loco Check Sheet(LAS)	33		
11.	-	Component History (LAS,ECS,ABS)	34-36		
12.	-	Component History & Testing Parameter (Bogie Shop)	37 - 38		
13	-	Warranty Conditions as per Tenders	39 -41		

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42043

Type of Locomotive: WAP-7/WAG-9HC

1.0 Continuity Test of the cables

Page: 1 of 27

1.1 Continuity Test of Traction Circuit Cables

As per cable list given in Para 1.3 of document no. 3 EHX 410 124, check the continuity with continuity tester and megger each cable to be connected between following equipment with 1000V megger.

From	То	Continuity (OK/Not OK)	Prescribed Megger Value (min)	Measured Megger Value
Filter Cubicle	Transformer	OK	100 ΜΩ	Soom
Filter Cubicle	Terminal Box of Harmonic Filter Resistor (Roof)	ok	100 ΜΩ	750m
Filter Cubicle	Earthing Choke	ok	100 ΜΩ	doone
Earthing Choke	Earth Return Brushes	ok	100 ΜΩ	750 MS
Transformer	Power Converter 1	ок	100 ΜΩ	800 ms
Transformer	Power Converter 2	oK	100 ΜΩ	750mm
Power Converter 1	TM1, TM2, TM3	oK	100 ΜΩ	800ms
Power Converter 2	TM4, TM5, TM6	ok	100 ΜΩ	800ms
Earth	Power Converter 1	ok	100 ΜΩ	750 MD
Earth	Power Converter 2	ok	100 ΜΩ	dooms

1.2 Continuity Test of Auxiliary Circuit Cables

As per cable list given in Para 1.4 of document no. 3 EHX 410 124, check the continuity with continuity meter and megger each cable to be connected between following equipment with the help of 1000V megger.

Signature of the JE/SSE/Harness

Signature of the JE/SSE/Loco Cabling

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

Type of Locomotive: WAP-7/WAG-9HC

Page: 2 of 27

From	То	Continuity(OK/ Not OK)	Prescribed Megger Value (min)	Measured Megger Value
Transformer	BUR1	02	100 ΜΩ	600 M/2
Transformer	BUR2	0/2	100 M Ω	500 mr
Transformer	BUR3	OK	100 ΜΩ	600 ma
Earth	BUR1	Olf	$100~ extsf{M}\Omega$	500 ma
Earth	BUR2	Oll	100 MΩ	COTO MA
Earth	BUR3	oK.	100 M Ω	con ma
BUR1	HB1	OK	100 MΩ	600 Mr
BUR2	HB2	OK	100 MΩ	Goo ma
HB1	HB2	oK	100 ΜΩ	600 ma
HB1	TM Blower 1	ok	$100~ extsf{M}\Omega$.	500 m/
HB1	TM Scavenge Blower 1	OK	100 ΜΩ	600 mg
HB1	Oil Cooling Unit 1	OK	100 MΩ	Ten mr
· HB1	Compressor 1	OK	100 MΩ	600 m
HB1	TFP Oil Pump 1	oK	100 MΩ	600 mr
HB1	Converter Coolant Pump 1	OK .	100 ΜΩ	600 mr
HB1	MR Blower 1	OK .	100 ΜΩ	600 mr
HB1	MR Scavenge Blower 1	OK	100 ΜΩ	700 m2
HB1	Cab1	OK	100 ΜΩ	600 mn
Cab1	Cab Heater 1	OK	100 ΜΩ	600mm
HB2	TM Blower 2	OK	100 ΜΩ	Forma
HB2	TM Scavenge Blower 2	OK	100 ΜΩ	600 ma
HB2	Oil Cooling Unit 2	OK	100 ΜΩ	700 m
HB2	Compressor 2	OK	100 ΜΩ	700 m
HB2	TFP Oil Pump 2	OR	$100\mathrm{M}\Omega$	600 m
HB2	Converter Coolant Pump 2	ok	100 MΩ .	600 M
HB2	MR Blower 2	OK	100 ΜΩ	700 M2
HB2	MR Scavenge Blower 2	OK	100 ΜΩ	600 Mr
HB2	Cab2	O(x	100 ΜΩ	600 M/L
Cab2	Cab Heater 2	OK	100 ΜΩ	Form

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42043

Type of Locomotive: WAP-7/WAG-9HC

1.3 Continuity Test of Battery Circuit Cables

Page: 3 of 27

Check continuity of following cables as per Para 2.3 of document no. 3 EHX 610 299

From	То	Condition	Continuity (OK/Not OK)
Battery (wire no 2093)	Circuit breakers 110- 2, 112.1-1, 310.4-1	By opening and closing MCB 112	ok
MCB 110	Connector 50.X7-1	By opening and closing MCB 110	ок
Battery (Wire no. 2052)	Connector 50.X7-2		ok
SB2 (Wire no 2050)	Connector 50.X7-3		ok

Close the MCB 112, 110, 112.1, and 310.4 and	Prescribed value	Measured
measure the resistance of battery wires 2093, 2052, 2050 with respect to the loco earth.	> 0.5 MΩ	Value <u>1</u> ΜΩ
Measure the resistance between 2093 & 2052, 2093 & 2050, 2052 &	Prescribed value:	Measured
2050	> 50 MΩ	Value MΩ

Commission the indoor lighting of the locomotive as per Sheet No 7A & 7B.

1.4 Continuity Test of Screened Control Circuit Cables

Check the continuity and isolation of the screen cable of the following circuits with the help of sheet no. mentioned against each as per document no. 3 EHX 610 299.

Screened control circuit cables for	Corresponding Sheet Nos.	Continuity & Isolation (OK/Not OK)
Battery voltage measurement	04B	OK
Memotel circuit of cab1 &2	10A	øk
Memotel speed sensor	10A	οK
Primary voltage detection	01A, 12A	ok.
Brake controller cab-1 & 2	06F, 06G	oK

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42043

Type of Locomotive: WAP-7/WAG-9HC

Page: 4 of 27

<u> </u>		
Master controller cab-1 &2	08C, 08D	OK
TE/BE meter bogie-1 & 2	08E, 08F	oK
Terminal fault indication cab-1 & 2	09F	ok
Brake pipe pressure actual BE electric	06Н	oK
Primary current sensors	12B, 12F	ok
Harmonic filter current sensors	12B, 12F	0K
Auxiliary current sensors	12B, 12F	ok
Oil circuit transformer bogie 1	12E, 12I	0K
Magnetization current	12C, 12G	o k
Traction motor speed sensors (2 nos.)	12D	•
and temperature sensors (1 no.) of TM-1		oK
Traction motor speed sensors (2nos)	12D	
and temperature sensors (1 no.) of TM-2		OK
Traction motor speed sensors (2nos)	12D	
and temperature sensors (1 no.) of TM-3		ok ·
Traction motor speed sensors (2 nos.)	12H	
and temperature sensors (1 no.) of TM-4		OK
Traction motor speed sensors (2nos)	12H	
and temperature sensors (1 no.) of TM-5		ok
Traction motor speed sensors (2nos)	12H	
and temperature sensors (1 no.) of TM-6		OK
Train Bus cab 1 & 2		0/
(Wire U13A& U13B to earthing	13A	
resistance=		
10K Ω ± ± 10%)		OK
UIC line	13B	OK
Connection FLG1-Box TB	13A	ok

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

42043

Type of Locomotive: WAP-7/WAG-9HC

Page: 5 of 27

2.0 Low Tension test

2.1 Measurement of resistor in OHMS (Ω)

Measure the resistances of the load resistors for primary voltage transformer, load resistors for primary current transformer and Resistor harmonic filter as per Para 3.2 of the document no. 3 EHX 610 279.

Name of the resistor	Prescribed value	Measured value
Load resistor for primary voltage transformer (Pos. 74.2).	3.9K Ω ± 10%	3.akV.
Resister to maximum current relay.	1 Ω ± 10%	IA
Load resistor for primary current transformer (Pos. 6.11).	$3.3 \Omega \pm 10\%$	3.31.
Resistance harmonic filter (Pos 8.3). Variation allowed \pm 10%	WAP7	WAP7
Between wire 5 & 6	0.2 Ω	0.21
Between wire 6 & 7	0.2 Ω	0.21
Between wire 5 & 7	0.4 Ω	0.41
For train bus, line U13A to earthing.	10 k Ω ± 10%	999KN'
For train bus, line U13B to earthing.	10 k Ω ± 10%	lo kn.
Insulation resistance of High Voltage Cable from the top of the roof to the earth (by1000 V megger).	200 ΜΩ	250 M A
Resistance measurement earth return brushes Pos. 10/1.	≤0.3 Ω	0.29 /
Resistance measurement earth return brushes Pos. 10/2.	≤0.3 Ω	0.29 A
Resistance measurement earth return brushes Pos. 10/3.	≤0.3 Ω	0.29 N
Resistance measurement earth return brushes Pos. 10/4.	≤0.3 Ω	0.29 1
Earthing resistance (earth fault detection) Harmonic Filter –I; Pos. 8.61.	2.2 kΩ± 10%	3.2KV.
Earthing resistance (earth fault detection) Harmonic Filter –II; Pos 8.62.	2.7 k Ω ± 10%	27KN
Earthing resistance (earth fault detection) Aux. Converter; Pos. 90.3.	3.9 k Ω ± 10%	3.9KN
Earthing resistance (earth fault detection) 415/110V; Pos. 90.41.	1.8 k Ω ± 10%	1.8KA.
Earthing resistance (earth fault detection) control circuit; Pos. 90.7.	390 Ω ± 10%	391)l·
Earthing resistance (earth fault detection) Hotel load; Pos. 37.1(in case of WAP5).	3.3 k Ω ± 10%	Big NA
Resistance for headlight dimmer; Pos. 332.3.	10 Ω ± 10%	100.

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU

Locomotive No.: 4204/3 Note: Type of Locomotive: WAP-7/WAG-9HC

Page : 6 of 27

Make sure that the earthing brush device don't make direct contact with the axle housing, earth connection must go by brushes.

2.2 Check Points

Items to be checked	Remarks
Check whether all the earthing connection in roof and machine room as mentioned in sheet no. 22A is done properly or not. These earthing connections must be flexible and should be marked yellow & green	Checked oK
Check whether all the earthing connection between loco body and bogie is done properly or not. These cables must be flexible having correct length and cross section	Cheukewok.

2.3 Low Tension Test Battery Circuits (without control electronics)

These tests are done with the help of the special type test loop boxes as per procedure given in Para 3.6 of the document no. 3 EHX 610 279

Name of the test	Schematic used.	Remarks
Test 24V supply	Sheet 04F and other linked sheets	cheeHeloK
Test 48V supply	Sheet 04F & sheets of group 09	Fan supply to be checked. のい・
Test traction control	Sheets of Group 08.	OK
Test power supply bus stations.	Sheets of Group 09.	Fan supply to be checked.
Test control main apparatus	Sheets of Group 05.	0K
Test earth fault detection battery circuit by making artificial earth fault to test the earth fault detection	Sheet 04C	OK
Test control Pneumatic devices	Sheets of Group 06	oK
Test lighting control	Sheets of Group 07	OK
Pretest speedometer	Sheets of Group 10	ok
Pretest vigilance control and fire system	Sheets of Group 11	OK
Power supply train bus	Sheets of Group 13	ok

10

PATIALA LOCOMOTIVE WORKS, PATIALA

Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU

40-4R

Type of Locomotive: WAP-7/WAG-9HC

Page: 7 of 27

LOCC	motive No.: $V^*/-$
3.0	Downloading of Software

3.1 Check Points.	Yes/No
Check that all the cards are physically present in the bus stations and all the plugs are connected.	YeJ
Check that all the fibre optic cables are correctly connected to the bus stations.	Yes
Make sure that control electronics off relay is not energized i.e. disconnect Sub-D 411.LG and loco is set up in simulation mode.	Ýej
Check that battery power is on and all the MCBs (Pos. 127.*) in SB1 &SB2 are on	yes.

3.2 Download Software

The software of Traction converter, Auxiliary converter and VCU should be done by commissioning engineer of the firm in presence of supervisor. Correct software version of the propulsion equipment to be ensured and noted:

Traction converter-1 software version:	792.09
Traction converter-2 software version:	792.09
Auxiliary converter-1 software version:	895.02_
Auxiliary converter-2 software version:	895.02
Auxiliary converter-3 software version:	895.02
Vehicle control unit -1 software version:	726.01
Vehicle control unit -2 software version:	726.01

3.3 Analogue Signal Checking

Check for the following analogue signals with the help of diagnostic tool connected with loco

Description	Signal name	Prescribed value	Measured
			Value
Brake pipe pressure	FLG2;0101XPrAutoBkLn	100% (= 5 Kg/cm2)	OK
Actual BE electric	FLG2; AMSB_0201- Wpn BEdem	100% (= 10V)	6K
TE/BE at 'o' position	FLG1; AMSB_0101- Xang Trans	Between 9% and 11%	
from both cab	FLG2; AMSB_0101- Xang Trans		10%.
TE/BE at 'TE maximal'	FLG1; AMSB_0101- Xang Trans	Between 99 % and 101 %	
position from both cab	FLG2; AMSB_0101- Xang Trans		kov.
TE/BE at 'TE minimal'	FLG1; AMSB_0101- Xang Trans	Between 20 % and 25 %	271
position from both cab	FLG2; AMSB_0101- Xang Trans		951

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 4243

Type of Locomotive: WAP-7/WAG-9HC

Page: 8 of 27

r			
TE/BE at 'BE maximal' position from both cab	XangTrans FLG2; AMSB_0101- XangTrans	Between 99% and 101%	1004.
TE/BE at 'BE Minimal' position from both cab	FLG1; AMSB_0101- XangTrans FLG2; AMSB_0101- XangTrans	Between 20% and 25%	254.
TE/BE at '1/3' position in TE and BE mode in both cab.	HBB1; AMS 0101- LT/BDEM>1/3 HBB2; AMS_0101- LT/BDEM>1/3	Between 42 and 44%	447.
TE/BE at '1/3' position in TE and BE mode in both cab.	HBB1; AMS_0101- LT/BDEM>2/3 HBB2; AMS_0101- LT/BDEM>2/3	Between 72 and 74%	747.
Both temperature sensor of TM1	SLG1; AMSB_0106- XAtmp1Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	19°C
Both temperature sensor of TM2	SLG1; AMSB_0106- Xatmp2Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	19°C.
Both temperature sensor of TM3	SLG1; AMSB_0106- Xatmp3Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	le°c
Both temperature sensor of TM4	SLG2; AMSB_0106- XAtmp1Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	195°c.
Both temperature sensor of TM5	SLG2; AMSB_0106- Xatmp2Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	/9°c
Both temperature sensor of TM6	SLG2; AMSB_0106- Xatmp3Mot	Between 10% to 11.7% depending upon ambient temperature 0°C to 40°C	1900

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42013

Type of Locomotive: WAP-7/WAG-9HC

Page: 9 of 27

3.4 Functional test in simulation mode

Conduct the following functional tests in simulation mode as per Para 5.5 of document no.3EHX 610 281. through the Diagnostic tool/laptop:

Test Function	Result desired in sequence	Result obtained
Emergency shutdown through	VCB must open.	
emergency stop switch 244	Panto must lower.	Cheekedok
Shut Down through cab activation	VCB must open.	
switch to OFF position	Panto must lower.	Clauesok
Converter and filter contactor	FB contactor 8.41 is closed.	
operation with both Power	By moving reverser handle:	
Converters during Start Up.	Converter pre-charging contactor	·
	12.3 must close after few seconds.	
	• Converter contactor 12.4 must close.	Cheurdok
·	Converter re-charging contactor	Check
	12.3 must opens.	
·	By increasing TE/BE throttle:	
	• FB contactor 8.41 must open.	,
· .	FB contactor 8.2 must close.	
	• FB contactor 8.1 must close.	
Converter and filter contactor operation with both Power Converters during Shut Down.		
Source and and ing office Bown.	Panto must lower.	Checkedon
	• Converter contactor 12.4 must open.	(semidiz
	• FB contactor 8.1 must open.	
	• FB contactors 8.41 must close.	·
	• FB contactor 8.2 must remain closed.	

~\u

Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42041

Type of Locomotive: WAP-7/WAG-9HC

Page: 10 of 27

		·
Contactor filter adaptation by	Isolate any one bogie through bogie)
isolating any bogie	cut out switch. Wait for self-test of	·
	the loco.	
•	• Check that FB contactor 8.1 is open.	
	 Check that FB contactor 8.2 is open. 	
	After raising panto, closing VCB, and	Checkedou
	setting TE/BE	4/0
	• FB contactor 8.1 closes.	,
	• FB contactor 8.2 remains open.	•
Test earth fault detection battery	By connecting wire 2050 to	
circuit positive & negative	earth, create earth fault	
	negative potential.	Clarkefore
	• message for earth fault	
	By connecting wire 2095	,
•	to earth, create earth	*
	fault positive potential.	
	message for earth fault	
Test fire system. Create a smoke in	When smoke sensor-1 gets	
the machine room near the FDU.	activated then \int	•
Watch for activation of alarm.	• Alarm triggers and fault	
	message priority 2	
•	appears on screen.	Cheredon
	When both smoke sensor	0 0 4 -
	1+2 gets activated then	
	A fault message priority	
	1 appears on screen and	
	lamp LSF1 glow.	
	Start/Running interlock occurs and /	
	TE/BE becomes to 0.	
ime, date & loco number	Ensure correct date time and Loco	
	number	OK
·		l

SIL

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u> IGBT based Traction Converter, Auxiliary Converter and TCN based VCU

Locomotive No.: 4043

Type of Locomotive: WAP-7/WAG-9HC

4.0 Sensor Test and Converter Test

Page: 11 of 27

4.1 Test wiring main Transformer Circuits

Apply $198V_p/140V_{RMS}$ to the primary winding of the transformer (at 1u; wire no. 2 at surge arrestor and at 1v; wire no. 100 at earthing choke). Measure the output voltage and compare the phase of the following of the transformers.

Output Winding nos.	Description of winding.	Prescribed Output Voltage & Polarity with input supply.	Measured output	Measured polarity
2U ₁ & 2V ₁	For line converter bogie 1 between cable 801A- 804A	10.05V _p and same polarity	10.05 VP	ok
2U ₄ & 2V ₄	For line converter bogie 1 between cable 811A- 814A	10.05V _p and same polarity	10.05 VP	OK
2U ₂ & 2V ₂	For line converter bogie 2 between cable 801B- 804B	10.05V _p and same polarity	10.04 VP.	OK
2U ₃ & 2V ₃	For line converter bogie 2 between cable 811B- 814B	10.05V _p and same polarity	10.0446.	OK
2U _B & 2V _B	For aux. converter 1 between cable 1103- 1117 (in HB1) For Aux converter 2 between cable 1103- 1117 (in HB2)	7.9V _p , 5.6V _{RMS} and same polarity.	7.8 VP.	OK
2U _F & 2V _F	For harmonic filter between cable 4-12 (in FB)	9.12V _p , 6.45V _{RMS} and same polarity.	9.11 VP. 6.44NAM.	Oh

4.2 Test wiring auxiliary transformer 1000V/415V-110V (pos. 67)

Apply $141V_p$ / $100V_{RMS}$ to input of the auxiliary transformer at cable no 1203 –1117 and measure the output at

Description of wire no.	Prescribed Output Voltage & Polarity with input supply.	Measured output	Measured polarity
Cable no. 1218 - 1200	58.7V _p , 41.5V _{RMS} and opposite polarity.	58-7NP.	OK
Cable no. 1218 – 6500	15.5V _p , 11.0V _{RMS} and opposite polarity.		OK_

HI LOVES.

سلالهم

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: They

Type of Locomotive: WAP-7/WAG-9HC

Page : 12 of 27

4.3 Primary Voltage Transformer

Apply $250V_{eff}/350V_p$ by variac to roof wire 1 and any wire 0 and measure the magnitude and polarity of the output of the primary voltage transformer for both bogies as per the procedure specified and suggested by the traction converter manufacturer. Primary voltage measurement converters (Pos. 224.1/*) & catenary voltmeter (Pos. 74/*)

This test is to be done for each converter.

Activate cab in driving mode and supply $200V_{RMS}$ through variac to wire no 1501 and 1502. Monitor the following parameters through Diagnostic tool and in catenary voltmeter.

Signal name	Prescribed value in catenary voltmeter	Prescribed value in Micview	Monitored value in catenary voltmeter	Monitored value in SR diagnostic tool
SLG1_G 87-XUPrim	25kV	250%	SIKV	25%
SLG2_G 87-XUPrim	25 kV	250%	V N S C	250%

Decrease the supply voltage below 140 V_{RMS} . VCB must open at this voltage. In this case the readings in Diagnostic Tool and catenary voltmeter will be as follows.

Signal name	Prescribed value in catenary voltmeter	Prescribed value in Micview	Monitored value in catenary voltmeter	Monitored value in SR diagnostic tool
SLG1 G 87-XUPrim	17kV	170%	17KV	1707.
SLG2_G 87-XUPrim	17 kV	170%	ITKV	1707

Reactivate VCB to on by increasing this voltage to 175% (17.5 kV).

Increase the supply to 240 V_{RMS} through variac. VCB must open at this voltage, In this case the readings in diagnostic tool and catenary voltmeter will be as follows:

Signal name	Prescribed value in catenary voltmeter	Prescribed value in Micview	Monitored value in catenary voltmeter	Monitored value in SR diagnostic tool
SLG1_G 87-XUPrim	30kV	300%	30 WV	Zeoy.
SLG2_G 87-XUPrim	30 kV	300%	Row	3ery

Reactivate VCB to on by decreasing this voltage to 290% (29 kV).

All

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42-43

Type of Locomotive: WAP-7/WAG-9HC

Page: 13 of 27

4.4 Minimum voltage relay (Pos. 86)

Functionality test:

Minimum voltage relay (Pos. 86) must be adjusted to approx 68%			
Activate loco in cooling mode. Check Power supply of 48V to minimum voltage relay. Disconnect primary voltage transformer (wire no. 1511 and 1512) from load resistor (Pos. 74.2) and connect variac to wire no. 1501 and 1502. Supply 200V _{RMS} through variac. In this case; <i>Minimum voltage relay (Pos. 86) picks up</i>	(Yés/No)		
Try to activate the cab in driving mode: Contactor 218 do not close; the control electronics is not be working.	(Yés/No)		
Turn off the variac : Contactor 218 closes; the control electronics is be working	(Yes/No)		
Test Under Voltage Protection			
Activate the cab in cooling mode; Raise panto; Supply 200V _{RMS} through variac to wire no. 1501 & 1502; Close the VCB; Interrupt the supply voltage The VCB goes off after 2 second time delay.	(Yes/No)		
Again supply $200V_{RMS}$ through variac to wire no. 1501 & 1502; Decrease the supply voltage below $140V_{RMS}\pm4V$; Fine tune the minimum voltage relay so that VCB opens.	(Yés/No)		

4.5 Maximum current relay (Pos. 78)	, ·
Disconnect wire 1521 & 1522 of primary current transfor &1522 (including the resistor at Pos. 6.11); Put loco in simula on contact 136.3; Close VCB; supply 3.6A _{RMS} at the open maximum current relay Pos. 78 for correct over current value	ation for driving mode; Open $R_3 - R_4$ wire 1521; Tune the drum of the
VCB opens with Priority 1 fault message on display.	(Yés/No)
Keep contact $R_3 - R_4$ of 136.3 closed; Close VCB; Tune the re-/9.9 A_p at the open wire 1521;	sistor 78.1 for the current of 7.0A _{RMS}
VCB opens with Priority 1 fault message on display.	(Yes/No)

-ile

Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: Your

Type of Locomotive: WAP-7/WAG-9HC

Page: 14 of 27

4.6 Test current sensors

Name of the sensor	Description of the test	Prescribed value	Set/Measured value
Primary return current sensor (Test-1,Pos.6.2/1 & 6.2/2)	Activate cab in driving mode supply 10A. Measure the current through diagnostic tool or measuring print.	(Variation allowed is ± 10%)	
Primary return current	Supply 90mA _{DC} to the test winding of sensor through connector 415.AA/1or 2 pin no. 7(+) & 8(-)		
sensor (Test-2, Pos.6.2/1 & 6.2/2)	Supply 297mA _{DC} to the test winding of sensor through connector 415.AA/1or 2 pin no. 7(+) & 8(-)		294mA
Auxiliary winding current sensor (Pos. 42.3/1 & 42.3/2)	Supply 90mA _{DC} to the test winding of sensor through connector 415.AC/1or 2 pin no. 7(+) & 8(-) Supply 333mA _{DC} to the test winding of		
	sensor through connector 415.AC/1 or 2 pin no. 7(+) & 8(-)		835MA
Harmonic filter current sensors (Pos.8.5/1 &8.5/2)	Supply 90mA _{DC} to the test winding of sensor through connector 415.AE/1or 2 pin no. 7(+) & 8(-)		—
	Supply 342mA _{DC} to the test winding of sensor through connector 415.AE/1or 2 pin no. 7(+) & 8(-)	-	245mp
Hotel load current sensors (Pos. 33/1 &	Switch on hotel load. Supply 90mA _{DC} to the test winding of sensor through connector 415.AG/1or 2 pin no. 7(+) & 8(-)	NA	MΑ
33/2)	Supply 1242mA _{DC} to the test winding of sensor through connector 415.AG/1or 2 pin no. 7(+) & 8(-)	MA	NA

du

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: May

Type of Locomotive: WAP-7/WAG-9HC

4.7 Test DC Link Voltage Sensors (Pos 15.6/*)

Page: 15 of 27

This test is to be done by the commissioning engineer of the firm if required.

4.8 Verification of Converter Protection Circuits (Hardware limits) -

This test is to be done as per para 6.17 of the document no. 3EHX 610 282 for both the converters.

Protection circuits	Limit on which shutdown should take place	Measured limit
Current sensors (Pos 18.2/1, 18.2/2, 18.2/3, 18.4/4, 18.5/1, 18.5/2, 18.5/3) for Power Converter 1	Increase the current quickly in the test winding of the current sensors, VCB will off at 2.52A with priority 1 fault for each sensor.	For 18.2/1= For 18.2/2= For 18.2/3= For 18.4/4= For 18.5/1= For 18.5/2= For 18.5/3=
Current sensors (Pos 18.2/1, 18.2/2, 18.2/3, 18.4/4, 18.5/1, 18.5/2, 18.5/3) for Power Converter 2	Increase the current quickly in the test winding of the current sensors, VCB will off at 2.52A with priority 1 fault for each sensor.	For 18.2/1= For 8.2/2= For 18.2/3= For 18.4/4= For 18.5/1= For 18.5/2= For 18.5/3=
Fibre optic failure In Power Converter1	Remove one of the orange fibre optic plugs on traction converter. VCB should trip	OV
Fibre optic failure In Power Converter2	Remove one of the orange fibre optic plugs on traction converter. VCB should trip	OK

4.9 Sequence of BUR contactors

The sequence of operation of BUR contactors for 'ALL BUR OK' BUR 1 out BUR 2 out and BUR 3 out condition has to be verified by putting the Loco in driving mode (VCB should not be closed) and isolating the BURs one by one. In these condition following will be the contactor sequence.

Status	52/1	52/2	52/3	52/4	52/5	52.4/1	52.4/2	52.5/1	52.5/2
Al BUR OK	Close	Open	Close	Open	Close	Open	Close	Close	Open
BUR1 off	Close	Open	Close	Close	Open	Close	Open	Open	Close
BUR2 off	Open	Open	Close	Close	Close	Close	Open	Open	Close
BUR3 off	Open	Close	Open	Close	Close	Close	Open	Open	Close

mle.

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
IGBT based Traction Converter, Auxiliary Converter and TCN based VCU

Locomotive No.: Yell

Type of Locomotive: WAP-7/WAG-9HC

Page: 16 of 27

Monitored contactor sequence

Status	52/1	52/2	52/3	52/4	52/5	52.4/1	52.4/2	52.5/1	52.5/2
AI BUR OK	close	open	Close	open	Close	open	close	Olose	Olon ·
BUR1 off	Clox	ofon	close.	close.	olen	Close	olon	open	Close
BUR2 off	olm	Olen	Class	Clore	Close	Clor	olon	ofen	Clarc
BUR3 off	open	Clore.	0600.	Close	dox	1 lose	المعاه	of Pn .	Close

5.0 Commissioning with High Voltage

5.1 Check List

Items to be checked	Yes/No
Fibre optic cables connected correctly.	Yes
No rubbish in machine room, on the roof, under the loco.	Yes
All the electronic Sub-D and connectors connected	YES
All the MCBs of the HB1 & HB2 open.	762
All the three fuses 40/* of the auxiliary converters	Yes
The fuse of the 415/110V auxiliary circuit (in HB1) open.	Yeu
Roof to roof earthing and roof to cab earthing done	YEI
Fixing, connection and earthing in the surge arrestor done correctly.	YEI
Connection in all the traction motors done correctly.	753
All the bogie body connection and earthing connection done correctly.	YES
Pulse generator (Pos. 94.1) connection done correctly.	YES
All the oil cocks of the gate valve of the transformer in open condition.	783
All covers on Aux & Power converters, Filter block, HB1, HB2 fitted	YEJ
KABA key interlocking system.	708

5.2 Safety test main circuit breaker

Prepare to switch off the catenary supply during the first charging of the locomotive in case of any unexpected behavior of the electrical component of the loco. Charge the loco for the first time by closing BLDJ switch. The VCB will trip after certain time as no oil/coolant pumps are running yet.

Perform the following safety test of main circuit breaker through both the cabs of the locomotive.

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: Yours

Type of Locomotive: WAP-7/WAG-9HC

Page: 17 of 27

Name of the test	Description of the test	Expected result	Monitored result
Emergency stop in cooling mode	Raise panto in cooling mode. Put the brake controller into RUN position. Close the VCB. Push emergency stop button 244.	VCB must open. Panto must lower. Emergency brake will be applied.	Charlote
Emergency stop in driving mode	Raise panto in driving mode in. Put the brake controller into RUN position. Close the VCB. Push emergency stop button 244.	VCB must open. Panto must lower. Emergency brake will be applied.	Clerko K
Under voltage protection in cooling mode	Raise panto in cooling mode. Close the VCB. Switch off the supply of catenary by isolator	VCB must open.	Clarkedol
Under voltage protection in driving mode	Raise panto in driving mode. Close the VCB. Switch off the supply of catenary by isolator	VCB must open with diagnostic message that catenary voltage out of limits	Cleerkeron
Shut down in cooling mode.	Raise panto in cooling mode. Close the VCB. Bring the BL- key in O position.	VCB must open. Panto must lower.	Aukedon
Shutdown in driving mode	Raise panto in driving mode. Close the VCB. Bring the BL- key in O position.	VCB must open. Panto must lower.	cheesed on
Interlocking pantograph- VCB in cooling mode	Raise panto in cooling mode. Close the VCB. Lower the pantograph by ZPT	VCB must open.	Clarked on
Interlocking pantograph- VCB in driving mode	Raise panto in driving mode. Close the VCB. Lower the pantograph by ZPT	VCB must open.	cluxedor

-JK

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42043

Type of Locomotive: WAP-7/WAG-9HC

Page: 18 of 27

5.3 Auxiliary Converter Commissioning

Switch on the high voltage supply and set up the loco in driving mode. Raise the panto. Close the VCB. Check that there is no earth fault in the auxiliary circuit, Switch off the VCB. Lower the panto. Create the earth fault in auxiliary circuit by making connection between wire no 1117(in HB2 cubicle) and earth. After 3 minutes a diagnostic message will come that "Earth fault auxiliary circuit."

5.3.1 Running test of 3 ph. auxiliary equipments

Switch on the 3 ph. auxiliary equipment one by one. Check the direction of rotation of each auxiliary machine and measure the continuous current and starting current drawn by them.

Name of the auxiliary machine	Typical phase current	Measured continuous phase current	Measured starting phase current
Oil pump transformer 1	9.8 amps	8.0	. 10.6
Oil pump transformer 2	9.8 amps	8.8	11.3
Coolant pump converter 1	19.6 amps	3.1	10.4
Coolant pump converter 2	19.6 amps	3.3	li Y
Oil cooling blower unit 1	40.0 amps	24.3	880
Oil cooling blower unit 2	40.0 amps	2419	88.5
Traction motor blower 1	34.0 amps	18.1	22.3
Traction motor blower 2	34.0 amps	18:2	56.3
Sc. Blower to Traction motor blower 1	6.0 amps	2.5	13.5
Sc. Blower to Traction motor blower 1	6.0 amps	2.6	140
Compressor 1	25 amps at 0 kg/ cm ² 40 amps at 10 kg/ cm ²	23.4	71.0
Compressor 2	25 amps at 0 kg/ cm ² 40 amps at 10 kg/ cm ²	21.2	85.0

-solv

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 4

Type of Locomotive: WAP-7/WAG-9HC

Page: 19 of 27

5.3.2 Performance of Auxiliary Converters

Measure the performance of the auxiliary converters through software and record it.

BUR1 (Condition: Switch off all the load of BUR 1)- to be filled by commissioning engineer

of the firm.

Signal name	Description of the signal	Prescribed value	Monitored value	Value under Limit (Yes/No)
BURI 7303 XUUN	Input voltage to BUR1	75% (10%=125V)	10011	165
BUR1 7303 XUUZ1	DC link voltage of BUR1	60% (10%=100V)	636	yes
BURI 7303 XUIZ1	DC link current of BUR1	0% (10%=50A)	(AMP	755.

BUR2 (Condition: Switch off all the load of BUR 2, Battery Charger on) to be filled by commissioning engineer of the firm.

Signal name	Description of the signal	Prescribed value by the firm	Monitored value	Value under Limit (Yes/No)
BUR2 7303-XUUN	Input voltage to BUR2	75% (10%=125V)	998. V	463
BUR2 7303-XUUZ1	DC link voltage of BUR2	60% (10%=100V)	6311	783
BUR2 7303-XUIZ 1	DC link current of BUR2	1% (10%=50A)*	7AM/	XEZ
BUR2 7303-XUILG	Current battery charger of BUR2	3% (10%=100A)*	diame	YET
BUR2 7303-XUIB1	Current battery of BUR2	1.5%(10%=100A)*	11 Am8	クロ
BUR2 7303 -XUUB	Voltage battery of BUR2	110%(10%=10V)	1101	153.

^{*} Readings are dependent upon charging condition of the battery.

BUR3 (Condition: Switch off all the load of BUR 3, Battery Charger on) to be filled by commissioning engineer of the firm.

Signal name	Description of the signal	Prescribed set value by the firm	Monitored value	Value under limit (Yes/No)
BUR3 7303-XUUN	Input voltage to BUR3	75% (10%=125V	999V	107
BUR3 7303- XUUZ1	DC link voltage of BUR3	60% (10%=100V)	637V	785
BUR3 7303-XUIZ 1	DC link current of BUR3	1% (10%=50A)*	7 Ams	965
BUR3 7303-XUILG	Current battery charger of BUR 3	3% (10%=100A)*	21Ans	405
BUR3 7303-XUIB1	Current battery of BUR 3	1.5%(10%=100A)*	11 AM	405
BUR3 7303-XUUB	Voltage battery of BUR 3	110%(10%=10V)	110 1	YES

^{*} Readings are dependent upon charging condition of the battery.

المالي المالي Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 42043

Type of Locomotive: WAP-7/WAG-9HC

Page: 20 of 27

5.3.3 Performance of BURs when one BUR goes out

When any one BUR goes out then rest of the two BURs should take the load of all the auxiliaries at ventilation level 3 of the locomotive.

Condition of BURs	Loads on BUR1	Loads in BUR2	Loads in BUR3
All BURs OK	Oil Cooling unit 1&2	TM blower1&2, TFP oil pump 1&2, SR coolant pump 1&2.	Compressor 1&2, Battery C charger and TM Scavenger blower 1&2
BUR 1 out		Oil Cooling unit 1&2, TM blower1&2, TM Scavenger blower 1&2	Compressor 1&2,TFP oil pump 1&2, SR coolant pump 1&2 and Battery charger.
BUR 2 out	Oil Cooling unit 1&2, TM blower 1&2; TM Scavenger blower 1&2		Compressor 1&2, TFP oil pump 1&2, SR coolant pump 1&2 and Battery charger.
BUR 3 out	Oil Cooling unit 1&2, TM blower1&2, TM Scavenger blower 1&2	Compressor 1&2, TFP oil pump 1&2, SR coolant pump 1&2 and Battery charger.	

5.4 Auxiliary circuit 415/110

For checking earth fault detection, make a connection between wire no. 1218 and vehicle body. On switching on VCB, Earth fault relay 89.5 must pick up and after 3 minutes a message will come in the Diagnostic display that Earth Fault 415/110V Circuit

Switch on the 1 ph. auxiliary equipment one by one. Check the direction of rotation of each auxiliary machine and measure the continuous current and starting current drawn by them.

Name of the auxiliary machine	Typical phase current	Measured phase current	Measured starting current
Machine room blower 1	15.0 amps*	4.5	15.5
Machine room blower 2	15.0 amps*	4.6	14.7
Sc. Blower to MR blower 1	1.3 amps	1.4	4.9
Sc. Blower to MR blower 2	1.3 amps	1.2	4.6
Ventilator cab heater 1	1.1 amps	1.0	2.6
Ventilator cab heater 2	1.1 amps	1.0	3.6
Cab heater 1	4.8 amps	4.7	4.8
Cab heater 2	4.8 amps	4.7	4-8

^{*} For indigenous MR blowers.

aful

Issue No.03 Effective Date: Feb 2022 Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: Moul

Type of Locomotive: WAP-7/WAG-9HC

Page: 21 of 27

5.5 Hotel load circuit (Not applicable for WAG-9HC)

For WAP-7 locomotive with Hotel load converter refer to Annexure-HLC

5.6 Traction Converter Commissioning

This test is carried out in association with Firm.

Traction converter commissioning is being done one at a time. For testing Converter 1, switch off the traction converter 2 by switch bogie cut out switch 154. For testing Converter 2, switch off the traction converter 2 by switch bogie cut out switch 154. Isolate the harmonic filter also by switch 160. Start up the loco by one converter. Follow the functionality tests.

For Converter 1

Test Function	Results desired	Result obtained	
Measurement of charging and pre-charging and charging of DC Link of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Cluedore	
Measurement of discharging of DC Link of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Clubel one	
Earth fault detection on positive potential of DC Link of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Clerkeson	
Earth fault detection on negative potential of DC Link of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Clerkedok	
Earth fault detection on AC part of the traction circuit of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	cheaked ou	
Pulsing of line converter of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Clekel ou	
Pulsing of drive converter of Converter 1	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Cleckel ole	

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

Toys

Type of Locomotive: WAP-7/WAG-9HC

Page: 22 of 27

For Converter 2

Test Function	Results desired in sequence	Result obtained
Measurement of charging and pre-charging and charging of DC Link of Converter 2	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Checked ok
Measurement of discharging of DC Link of Converter 2	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Checked OK
positive potential of DC Link of Converter 2.	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Ohecked ok
negative potential of DC Link of Converter 2.	Traction converter manufacturer to declare the successful operation and demonstrate the same to the supervisor/v	Checked OL
Earth fault detection on AC part of the traction circuit of Converter 2.	declare the successful operation and demonstrate the same to the PLW supervisor.	Checked ox
of Converter 2.	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Checkelok
Pulsing of drive converter of Converter 2	Traction converter manufacturer to declare the successful operation and demonstrate the same to the PLW supervisor.	Cheched OLL

Issue No.03

Effective Date: Feb 2022

Doc.No.F/ECS/01

(Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

your

Type of Locomotive: WAP-7/WAG-9HC

Page: 23 of 27

5.7 Test protective shutdown SR

Test Function	Results desired in sequence	Result obtained
Measurement of protective shutdown by Converter 1 electronics.	Start up the loco with both the converter. Raise panto. Close VCB. Move Reverser handle to forward or reverse. Remove one of the orange fibre optic feedback cable from converter 1Check that converter 1 electronics produces a protective shut down. • VCB goes off • Priority 1 fault mesg. on DDU appears Disturbance in Converter 1	Checkelox
Measurement of protective shutdown by Converter 2 electronics.	Start up the loco with both the converter. Raise panto. Close VCB. Move Reverser handle to forward or reverse. Remove one of the orange fibre optic feedback cable from converter 2. Check that converter 2 electronics produces a protective shut down. • VCB goes off • Priority 1 fault mesg. on diagnostic display appears Disturbance in Converter 2	Checkelou

5.8 Test Harmonic Filter

Switch on the filter by switch 160

Test Function	Results desired in sequence	Result obtained
currents	Start up the loco with both the converter. Raise panto. Close VCB. Move Reverser handle to forward or reverse. Apply a small value of TE/BE by moving the throttle. • FB contactor 8.41 must open.	Cheekelok

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

Your

Type of Locomotive: WAP-7/WAG-9HC

Page: 24 of 27

Test earth fault	 FB contactor 8.2 must close. FB contactor 8.1 must close Check the filter current in diagnostic laptop Bring the TE/BE throttle to O Switch off the VCB FB contactor 8.1 must open. FB discharging contactor 8.41 must close Check the filter current in diagnostic laptop Make a connection between wire 	Checkedok
detection harmonic filter circuit.	no. 12 and vehicle body. Start up the loco. Close VCB. • Earth fault relay 89.6 must pick up. • Diagnostic message comes that - Earth fault in harmonic filter circuit	Checkedole
Test traction motor speed sensors for both bogie in both cabs	Traction converter manufacturer to declare the successful operation and demonstrate the same to the supervisor/ PLW	OK.

5.9 Test important components of the locomotive

Items to be tested	Description of the test	Monitored value/remarks
Speedometer	VCU converter manufacturer to declare the successful operation and demonstrate the same to the supervisor/ PLW	Cheeked ou
Time delay module of MR blower	The time after which the starting capacitor for MR blower should go off the circuit should be set to 10-12 seconds	Cheekel ok
Ni-Cd battery voltage	At full charge, the battery voltage should be 110V DC.	checkelou
Flasher light	From both cab flasher light should blink at least 65 times in one minute.	Cheekel OK
Head light	Head light should glow from both cabs by operating ZLPRD. Dimmer operation of headlight should also occur by operating the switch ZLPRD.	Checholac

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.:

yours

Type of Locomotive: WAP-7/WAG-9HC

Page: 25 of 27

Marker light	Both front and tail marker light should glow from both the cabs	chedrolac
Cab Light	Cab light should glow in both the cabs by operating the switch ZLC	Checked at
Spot lights	Both Drivers and Asst. Drivers Spot light should glow in both cabs by operating ZLDD	Checkelok
Instrument lights	Instrument light should glow from both cab by operating the switch ZLI	chellost re
Illuminated Push button	All illuminated push buttons should glow during the operation	Chelled one Cheket one
Contact pressure of the high rating contactors	The contact pressure of FB contactors (8.1, 8.2) is to be measured Criteria: The minimum contact pressure is 54 to 66 Newton.	For contactor 8.1:7 For contactor 8.2:
Crew Fan	All crew fans should work properly when VCB of the loco is switched on. The airflow from each cab fan is to be measured. Criteria: The minimum flow of air of cab fan should be 25 m ³ /minute	Cab 1 LHS: Cab 1 RHS: Cab 2 LHS: Cab 2 RHS:

6.0 Running Trial of the locomotive

SN	Description of the items to be seen during trail run	· · · · · · · · · · · · · · · · · · ·			
1	Cab activation in driving mode	No fault message should appear on the diagnostic panel of the loco.	Chellel on		
	Loco charging	Loco to be charged and all auxiliaries should run. No fault message to appear on the diagnostic panel of the loco. Raise MR pressure to 10 Kg/cm ² , BP to 5 Kg/cm ² , FP to 6 Kg/cm ² .	Clevelox		
3.	Check function of Emergency push stop.	This switch is active only in activated cab. By pushing this switch VCB should open & pantograph should be lowered.	Cleveson		
4.	Check function of BPCS.	 Beyond 5 kmph, press BPCS, the speed of loco should be constant. BPCS action should be cancelled by moving TE/BE throttle, by dropping BP below 4.75 Kg/cm², by pressing BPCS again. 	Cleueson		
5.	Check train parting operation of the Locomotive.	Operate the emergency cock to drop the BP Pressure LSAF should glow.	Cleven		

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: Your

Type of Locomotive: WAP-7/WAG-9HC

Page: 26 of 27

6.	Check vigilance	Set the speed more than 1.5 kmph and ensure that	
	operation of the	brakes are released i.e. BC < 1 Kg/cm ² .	
	locomotive	For 60 seconds do not press vigilance foot switch or	
		sanding foots switch or TE/BE throttle or BPVG	
	·	switch then	
		Buzzer should start buzzing.	
		LSVW should glow continuously.	
		Do not acknowledge the alarm through BPVG or	
		vigilance foot switch further for 8 seconds then:-	
		Emergency brake should be applied	
		automatically.	[1]
		VCB should be switched off.	Vevel of
		Resetting of this penalty brake is possible only after	
	`	32 seconds by bringing TE/BE throttle to 0 and	
		acknowledge BPVR and press & release vigilance	
		foot switch.	
7.	Check start/run interlock	• At low pressure of MR (< 5.6 Kg/cm ²).	
÷		With park brake in applied condition.	N.Y.
		• With direct loco brake applied (BP< 4.75Kg/cm ²).	
		• With automatic train brake applied (BP<4.75Kg/cm ²).	Chekelo
		• With emergency cock (BP < 4.75 Kg/cm ²).	character of
8.	Check traction interlock	Switch of the brake electronics. The	
		Tractive /Braking effort should ramp down, VCB	chowa ("
		should open and BP reduces rapidly.	
9.	Check regenerative	Bring the TE/BE throttle to BE side. Loco speed	Cherolo
	braking.	should start reducing.) Character
10.	Check for BUR	In the event of failure of one BUR, rest of the two	
	redundancy test at	BURs can take the load of all the auxiliaries. For this	- 0 m o 1 0
	ventilation level 1 & 3 of	switch off one BUR.	church o
	loco operation	Auxiliaries should be catered by rest of two BURs.	
4.4		Switch off the 2 BURs; loco should trip in this case.	
11.	Check the power	Create disturbance in power converter by switching	
	converter	off the electronics. VCB should open and converter	creeked &
	isolation test	should get isolated and traction is possible with	
		another power converter.	

Effective Date: Feb 2022

Doc.No.F/ECS/01 (Ref: WI/ECS/10)

PATIALA LOCOMOTIVE WORKS, PATIALA

<u>Testing & Commissioning Format For 3-Phase Locomotive fitted with</u>
<u>IGBT based Traction Converter, Auxiliary Converter and TCN based VCU</u>

Locomotive No.: 420 43

Type of Locomotive: WAP-7/WAG-9HC

Page: 27 of 27

7.0 Final check list to be verified at the time of Loco dispatch

Condition /Operations of the following items are to be checked:

SN	Item	Cab-1	Cab-2	Remarks
1	Head lights	Ou_	an 9	And the second second
2	Marker Red	on_	OL	
3	Marker White	٥٥	ON	
4	Cab Lights	92	છેમ	
5	Dr Spot Light	ðv	ese (·
6	Asst Dr Spot Light	<u>o@</u>	ં શ્વેષ	Thousand worker way
7	Flasher Light	0.4	અ	Challand Woodle 1974
8	Instrument Lights	Od	en,	
9	Corridor Light	â.	on,	
10	Cab Fans	or_	OR	
11	Cab Heater/Blowers	200	, Ko	
12	All Cab Signal Lamps Panel 'A'	9~	6 0	

Status of RDSO modifications

LOCO NO: 42043.

3n	Modification No.	Description	Remarks
1.	RDSO/2008/EL/MS/0357	Modification in control circuit of Flasher Light and Head Light of	Ok/Not Ok
	Rev.'0' Dt 20.02.08	three phase electric locomotives.	
.	RDSO/2009/EL/MS/0377 Rev.'0' Dt 22.04.09	Modification to voltage sensing circuit in electric locomotives.	Ok/Not Ok
	RDSO/2010/EL/MS/0390 Rev.'0' Dt 31.12.10	Paralleling of interlocks of EP contactors and Relays of three phase locomotives to improve reliability.	Ok/Not Ok
-	RDSO/2011/EL/MS/0399	Removal of interlocks of control circuit contactors no. 126 from	Ok/Not Ok
	Rev.'0' Dt 08.08.11 RDSO/2011/EL/MS/0400 Rev.'0' Dt 10.08.11	Modification sheet for shifting the termination of \$GKW, 1.8 KV, 70 sq mm cables and 2x2.5 sq mm cables housed in lower portion of HB2 panel and provision of Synthetic resin bonded glass fiber sheet for three phase locomotives.	Ok/Not Ok
 }.	RDSO/2011/EL/MS/0401 Rev.'0' Dt 10.08.11	Modification sheet for relaying of cables in HB-2 panel of three	Ok/Not Ok
· .	RDSO/2011/EL/MS/0403 Rev.'0' Dt 30.11.11	Auto switching of machine room/corridor lights to avoid draining or hatteries in three phase electric locomotives.	Ok/Not Ok
3.	RDSO/2012/EL/MS/0408 Rev.'0'	Modification of terminal connection of heater cum blower	Ók/Not Ok
)	RDSO/2012/EL/MS/0411 Rev.'1' dated 02.11.12	Modification sheet to avoid simultaneous switching ON or write and Red marker light in three phase electric locomotives.	Ók/Not Ok
10	RDSO/2012/EL/MS/0413 Rev.'1' Dt 25.04.16	Paralleling of interlocks of EP contactors and auxiliary contactors of three phase locomotives to improve reliability.	Ŏk/Not Ok
11	RDSO/2012/EL/MS/0419 Rev.'0' Dt 20.12.12	Modification sheet to provide rubber sealing gasket in waster	Ok/Not Ok
12	RDSO/2013/EL/MS/0420 Rev.'0' Dt 23.01.13	Modification sheet to provide mechanical locking arrangement in Primary Over Current Relay of three phase locomotives.	Ok/Not Ok
13	RDSO/2013/EL/MS/0425 Rev.'0' Dt 22.05.13	Modification sheet for improving illumination of head light in dimmer mode in three phase electric locomotives.	Ok/Not Ok
14	RDSO/2013/EL/MS/0426 Rev.'0' Dt 18.07.13	Modification sheet of Bogie isolation rotary switch in three phase	Ók/Not Ok
15	RDSO/2013/EL/MS/0427 Rev.'0' Dt 23.10.13	Modification sheet for MCP control in three phase electric	Ok/Not Ok
16	RDSO/2013/EL/MS/0428 Rev.'0' Dt 10.12.13	Modification sheet for relocation of earth fault relays for harmonic filter and hotel load along with its resistors in three phase electric locomotives	Ok/Not Ok
17	RDSO/2014/EL/MS/0432 Rev.'0' Dt 12.03.14	Removal of shorting link provided at c-d terminal of over current	
18		Provision of Auxiliary interlock for monitoring of Harmonic filler ON (8.1) edeption (8.2) Contactor in GTO/IGBT locomotives.	Ok/Not Ok
19		7 Modification in blocking diod as to improve reliability in timee phase	 /
20		- /OF\ *** ofting conomo	Ok/Not Ok
21		7 Implementation of push pull scheme.	Ok/Not Ok
22	RDSO/2024/EL/MS/050 Rev '0' Dt. 13.09.2024	by Loco Pilot in case of emirgency with time stamping in VCO o	OKINGE OK
23	RDSO/2024/EL/MS/050 Rev '0' Dt 10.10.2024	2 Unloader valve control circu modification in three Phase Electric Locomotives.	Ok/Not Ok
24	RDSO/2024/EL/MS/050 Rev '0' Dt 17.09.2024	reliability of three phase electric locomotives	
25	RDSO/2024/EL/MS/050 Rev '0' Dt 21.11.2024	Isolation of Harmonic Filter from 3-phase locomotives fitted with M/s Alstom (BTIPL), CGPISL and Medha make IGBT based Propulsion Equipment	Ok/Not Ok



Signature of JE/SSE/ECS

Loco No.: 42043

PLW/PATIALA

PNEUMATIC TEST PARAMETERS OF 3-PHASE ELECTRIC LOCOMOTIVES

(As per DG/RDSO/LKO's letter No.-EL/3.2.19/3phase, dated-29.03.2012)

SN	Parameters	Reference	Value	Result
	Brake Panel: M/s Faiveley			
1.0	Auxiliary Air supply system (Pantograph & VCB)			
1.1	Ensure, Air is completely vented from pantograph			0
	Reservoir (Ensure Panto gauge reading is Zero)			
1.2	Turn On BL Key. Now MCPA starts.		60 sec. (Max.)	59 sec
	Record pressure Build up time (8.0 kg/cm2)			
1.3	Auxiliary compressor safety Valve 23F setting	Faiveley Doc. No.	8.5±0.25kg/cm2	8.55 Kg/cm2
		DMTS-014-1, 8 CLW's	-	
		check sheet no.		
		F60.812 Version 2		
1.4	Check VCB Pressure Switch Setting	CLW's check sheet	Opens 4.5±0.15	4.55 Kg/cm2
		no. F60.812 Version 2	kg/cm2, closes	
			5.5±0.15 kg/cm2	5.55 Kg/cm2
1.5	Set pantograph Selector Switch is in Auto, Open pan-1&2 Is	solating Cocks & KABA co		
1.6	Set Cab-1 Pan UP in Panel A.		Observed Pan-2	ОК
			Rises.	
1.7	Close Pan-2 isolating Cock		Panto-2 Falls Down	ОК
	Open Pan -2 isolating Cock		Panto-2 Rises	
1.8	Record Pantograph Rise time		06 to 10 seconds	8 Sec
1.9	Record Pantograph Lowering Time		06 to 10 seconds	9 Sec
1.10	Panto line air leakage		0.7 kg/cm2 in 5	0.10 kg/cm2
			Min.	in 5 Min.
1.11	High Reach Panto emergency test and reset.			ok
2.0	Main Air Supply System			
2.1	Ensure, Air is completely vented from locomotive. Drain	Theoretical		
	out all the reservoirs by opening the drain cocks and then	calculation and		
	closed drain cocks. MR air pressure build up time by each	test performed by		
	compressor from 0 to 10 kg/cm2.	Railways.	.,	6 . 0.50
	i) with 1750 LPM compressor		i) 7 mins Max.	6 min. & 50
	ii) with 1450 LPM compressor		ii) 8.5 mins Max.	sec.
2.2	Drain air below MR 8 kg/cm2 to start both the		Check Starting of	ok
	compressors		both compressors	
2.3	Drain air from main reservoir up to 7 kg/cm2. Start		30 Sec. (Max)	CP1-29 Sec
	compressors, Check pressure build time of individual			
	compressor from 8 kg/cm2 to 9 kg/cm2			CP2-28 Sec
2.4	Check Low MR Pressure Switch Setting (37)	D&M test spec.	Closes at 6.40±0.15	6.50 Kg/cm2
		MM3882 &	kg/cm2 Opens at	
		MM3946	5.60±0.15kg/cm2	5.65 Kg/cm2
2.5	Check compressor Pressure Switch RGCP setting (35)	D&M test spec.	Opens at 10±0.20	10 Kg/cm2
		MM3882 &	kg/cm2, Closes	
		MM3946	at 8±0.2kg/cm2	8 Kg/cm2
2.6	Run both the compressors Record Pressure build up time	Trial results	3.5 Minutes Max.	3.45 minute

PLW/PATIALA

Loco No.: 42043

2.8 Check Auto Drain Valve functioning (124 & 87)	2.7	Check unloader val	ve operation				OK/Not OK	ОК
Direct by BLCP	2.8						Compressor	-
	2.9		safety valve setting	(10/1). Run CP	-			11.5 Kg/cm2
valve to reset at pressure 1.2 kg/cm2 less than opening pressure. 2.12 BP Pressure: Switch 'OFF' compressor, Drain MR Pressure by drain cock of 1" Main Reservoir, Start Compressor, check setting pressure of Duplex Check Valve 92F. 2.13 FP pressure: FF pressure: FF pressure: FF pressure: FF pressure in Gauge. 3.0 Air Dryer Operation 3.1 Open Drain Cock 90 of 2"d MR to start Compressor, leave open for Test Check Air Dryer Towers to change. 3.2 Check Purge Air Stops from Air Dryer at Compressor stops 3.3 Check condition of humidity indicator 4.0 Main Reservoir Leakage Test 4.1 Put 10 Brake (A-9) in full service, Check MR Pressure air leakage from both cabs. Check BP Air leakage (isolate BP charging cock-70) Brake Test (Automatic Brake operation) 5.1 Record Brake Pipe & Brake Cylinder pressure at Each Step Check proportionality of Auto Brake system CLW's check sheet no. F60.812 Version 2 CLW's check sheet no. F60.812 Version 2 Tower to change every minute Tower to change every minute Blue Blue Blue Blue Blue Blue Blue Blue Blue Check BP Air leakage (isolate BP charging cock-70) D&M test spec. MM3882 & MM3946 M3882 & MM3946 Check BP Air leakage (isolate BP charging cock-70) D&M test spec. MM3882 & MM3946 Should be less than 1 kg/cm2 in 15 minutes Minutes 5.0 Brake Test (Automatic Brake operation) F60.812 Version 2 CLW's check sheet no. F60.812 Version 2 Cleck proportionality of Auto Brake system CLW's check sheet no. F60.812 Version 2 CLW's check sheet n	2.10	direct by BLCP		· ·			11.5 Kg/cm2	
by drain cock of 1" Main Reservoir, Start Compressor, check setting pressure of Duplex Check Valve 92F. 2.13 FP pressure:	2.11	valve to reset at pressure 1.2 kg/cm2 less than opening						
Pr pressure:	2.12	BP Pressure: Switch 'OFF' compressor, Drain MR Pressure by drain cock of 1" Main Reservoir, Start Compressor,				5.0±0.10kg/cm2	5.0 Kg/cm2	
3.1 Open Drain Cock 90 of 2 nd MR to start Compressor, leave open for Test Check Air Dryer Towers to change. 3.2 Check Purge Air Stops from Air Dryer at Compressor stops 3.3 Check condition of humidity indicator 4.0 Main Reservoir Leakage Test 4.1 Put Auto Brake (A-9) in full service, Check MR Pressure air leakage from both cabs. 4.2 Check BP Air leakage (isolate BP charging cock-70) Brake Test (Automatic Brake operation) 5.0 Brake Test (Automatic Brake operation) Check proportionality of Auto Brake system Clw's check sheet no. F60.812 Version 2 Auto controller position BP Pressure kg/cm2 BC (WAG-9 & WAP-7) Kg/cm2 BC (WAG-9 & WAP-7) Kg/cm2 Auto controller Result Value Result Value Result Value Result Value Result Value Result Full service 3.35±0.2 3.4 Kg/cm2 2.50±0.1 2.5Kg/cm2 5.15±0.30	2.13	FP pressure: Fit Test Gauge in Test point 107F FPTP. Open isolate cock				6.0±0.20kg/cm2		
Open for Test Check Air Dryer Towers to change. Every minute	3.0	Air Dryer Operati	ion					
3.3 Check condition of humidity indicator Blue Blue	3.1	·		• •				ok
Main Reservoir Leakage Test	3.2	Check Purge Air Sto	ps from Air Dryer at	t Compressor stops				
A.1	3.3	Check condition of	humidity indicator				Blue	Blue
leakage from both cabs.	4.0	Main Reservoir Lea	akage Test					
MM3882 & MM3946 minutes Kg/cm2 in 5 minutes	4.1				-	than 1 kg/cm2 in	in 15	
Check proportionality of Auto Brake system	4.2	Check BP Air leakage (isolate BP charging cock-70)		-		_	Kg/cm2 in 5	
Check proportionality of Auto Brake system	5.0	Brake Test (Auto	matic Brake opera	ation)				
Auto controller position BP Pressure kg/cm2 BC (WAG-9 & WAP-7) BC (WAP-5) Kg/cm2 Kg/cm2 Kg/cm2 Kg/cm2 Kg/cm2 Kg/cm2 Result Value Result Value Result Value Result Run 5±0.1 5.0 Kg/cm2 0.00 0.00 Kg/cm2 0.00 - Intial 4.60±0.1 4.6 Kg/cm2 0.40±0.1 0.40Kg/cm2 0.75±0.15 - Full service 3.35±0.2 3.4 Kg/cm2 2.50±0.1 2.5 Kg/cm2 5.15±0.30 - Interpretation 4.50±0.20 4.50±0	5.1							
position Kg/cm2 Kg/cm2 Value Result Value Result Run 5±0.1 5.0 Kg/cm2 0.00 0.00 Kg/cm2 0.00 Intial 4.60±0.1 4.6 Kg/cm2 0.40±0.1 0.40Kg/cm2 0.75±0.15 - Full service 3.35±0.2 3.4 Kg/cm2 2.50±0.1 2.5Kg/cm2 5.15±0.30 -		Check proportional						
Run 5±0.1 5.0 Kg/cm2 0.00 0.00 Kg/cm2 0.00 - Intial 4.60±0.1 4.6 Kg/cm2 0.40±0.1 0.40Kg/cm2 0.75±0.15 - Full service 3.35±0.2 3.4 Kg/cm2 2.50±0.1 2.5Kg/cm2 5.15±0.30 -			BP Pressure kg/cm2		1	0 & WAP-7)	, ,	
Intial 4.60±0.1 4.6 Kg/cm2 0.40±0.1 0.40Kg/cm2 0.75±0.15 - Full service 3.35±0.2 3.4 Kg/cm2 2.50±0.1 2.5Kg/cm2 5.15±0.30 -			Value	Result	Value	Result	Value	Result
Intial 4.60±0.1 4.6 kg/cm2 0.40±0.1 0.40kg/cm2 0.75±0.15 - Full service 3.35±0.2 3.4 kg/cm2 2.50±0.1 2.5kg/cm2 5.15±0.30 -		Run	5±0.1	5.0 Kg/cm2	0.00	0.00 Kg/ cm2	0.00	-
5. 2.5kg till2		Intial	4.60±0.1	4.6 Kg/cm2	0.40±0.1		0.75±0.15	-
Emergency Less than 0.3 0.2 Kg/cm2 2.50±0.1 2.5Kg/cm2 5.15±0.30 -		Full service	3.35±0.2	3.4 Kg/cm2	2.50±0.1	2.5Kg/ cm2	5.15±0.30	-
<u> </u>		Emergency	Less than 0.3	0.2 Kg/cm2	2.50±0.1	2.5Kg/ cm2	5.15±0.30	-

PLW/PATIALA

Loco No.: 42043

5.2	Record time to BP pressure drop to 3.5 kg/cm2 Ensure	D&M test spec.	8±2 sec.	9 Sec
	Automatic Brake Controller handle is Full Service from Run	MM3882 & MM3946		
5.3	Operate Asst. Driver Emergency Cock,	D&M test spec.	BP pressure falls	
		MM3882 & MM3946	to Below 2.5	OK
		0.544 1 1 1 1	kg/cm2	1.00
5.4	Check brake Pipe Pressure Switch 69F operates	CLW's check sheet no.	Closes at BP	4.30
		F60.812 Version 2	4.05- 4.35	Kg/cm2
			kg/cm2	
			Opens at BP	2.05
			2.85- 3.15	3.05
	Maria Arita Braha Cantrallar handla franc Braning to	DOM took on a	kg/cm2	Kg/cm2
5.5	Move Auto Brake Controller handle from Running to	D&M test spec.		
	Emergency BC filling time from 0.4 kg/cm2 i.e. 95% of	MM3882 & MM3946		
	Max. BC developed		4±1 sec.	
	WAP5 – BC 5.15 ± 0.3 kg/cm2 apply time			
	WAP7 - BC 2.50 ± 0.1 kg/cm2 WAG9 - BC 2.50 ± 0.1 kg/cm2		7.5±1.5 sec. 21±3 sec.	20 Sec.
5.6	Move Auto Brake Controller handle to full service and	DOM tost spec	2113 Sec.	20 300.
5.0		D&M test spec. MM3882 & MM3946		
	BP pressure 3.5 kg/cm2. Move Brake controller to	1011013882 & 1011013946		
	Running position BC Release time to fall BC Pressure up			
	to 0.4 kg/cm2 i.e. 95% of Max. BC developed BC release Time			
	WAP7		17.5±25 sec.	
	WAG9		17.5±25 sec.	55 sec.
5.7	Move Auto Brake Controller handle to Release, Check	CLW's check sheet no.	60 to 80 Sec.	79 Sec.
5.7	·	F60.812 Version 2	60 to 80 sec.	79 Sec
г о	BP Pressure Steady at 5.5± 0.2 kg/cm2 time. Auto Brake capacity test: The capacity of the A9 valve		DD management	
5.8	in released condition must conform to certain limit in	RDSO Motive power	BP pressure should not fall	
		Directorate report no.		
	order to ensure compensation for air leakage in the	MP Guide No. 11 July, 1999 Rev.1	below 4.0 kg/cm2 with in	4.5
	train without interfering with the automatic	1999 Kev.1	60 Sec.	
	functioning of brake.		ou sec.	Kg/cm2
	* Allow The MR pressure to build up to maximum stipulated limit.			
	* Close brake pipe angle cock and charge brake pipe to			
	5 kg/cm2 by A-9 (Automatic brake controlling) at run			
	position.			
	* Couple 7.5 dia leak hole to the brake hose pipe of			
	locomotive. Open the angle cock for brake pipe.			
	The test shall be carried out with all the compressors in			
	working condition.			
5.9	Keep Auto Brake Controller (A-9) in Full Service. Press		BC comes to '0'	0
5.5	Driver End paddle Switch (PVEF)		De comes to 0	
6.0	Direct Brake (SA-9)			
6.1	Apply Direct Brake in Full Check BC pressure			
0.1	WAG9/WAP7	CLW's check sheet no.	3.5±0.20 kg/cm2	3.6
	WAG9/WAP7	F60.812 Version 2	5.15±0.3 kg/cm2	Kg/cm2
6.2			8 sec. (Max.)	8 Sec
0.2	Apply Direct Brake, Record Brake Cylinder charging	D&M test spec. MM3882 & MM3946	o Sec. (IVIdX.)	0 360
	time	1V11V13002 & 1V11V13940	1	

PLW/PATIALA

Loco No.: 42043

6.3	Check Direct Brake Pressure switch 59 (F)	D&M test spec. MM3882 & MM3946	0.2.±0.1 kg/cm2	0.25 kg/cm2
6.4	Release direct brake & BC Release time to fall BC pressure up to 0.4 kg/cm2		10 -15 Sec.	14 Sec
7.0	Modified System Software (only for CCB)		-NA-	-NA-
7.1	Bail-off de-activated during emergency by any means	-		
7.2	DPWCS and Non-DPWCS mode enabled		Multi Loco	
7.3	TCAS and Non-TCAS mode enabled		Not Yet Launched	Presently
7.4	Penalty brake application deactivated for Fault code 113 (FC 113) and CCB health signal will not drop to avoid loco detention/failure. The Brake Electronics Failure "message will not generate on DDS.	RDSO letter no.	Pressure Setting Needed is12 kg/sqcm causing mismatching with standard Pr Setting	not happening in PLW
7.5	CCB health signal logic revised (Now will remain high) for penalty condition occurring with FC 108 due to wrong operation/not affecting operation/ Not a CCB Fault (i.e Both controllers selected as LEAD etc) The Brake electronic failure message will not generate on DDS	EL/3.2.19/3-phase (CCB), dtd 30.01.2023	-NA-	-NA-
7.6	CCB health signal logic for FC 102 (In case of BC request from VCU is more than 90 %-above 9V DC) is changed i.e CCB health signal will not drop for FC 102 which will avoid loco detention/failure. The brake electronic failure message will not generate on DDS.		Could not performed by M/s Knorr	Presently Not happening in PLW
7.7	Booting time for CCB with TCAS/TPM/PTWS/DPWCS mode 15-20 sec. However, in case of absence of either one or both system booting time subsequently increased to 40-50 sec.		-NA-	-NA-
8.0	Sanding Equipment			
8.1	Check Isolating Cock-134F is in open position. Press sander paddle Switch. (To confirm EP valves Operates)		Sand on Rail	Ok
9.0	Test Vigilance equipment : As per D&M test specification			Ok

Signature of SSE/Shop

				42043			
	ROOF COMPONENT CAB 1 & 2						
S.No.	Description	PL NO.	QPL /Nos.	Supplier	Sr. no.		
1	Pantograph	29880014(HR), 29880026	2	FAIVELEY, CONTRANSYS	C25-1229/MAR-2025, 16181-02/25		
2	Servo motor	29880026	2	CONTRANSYS	14872-07/24		
3	Air Intake filter Assly	29480103	2	Vikrant	3297-08/2024, 3602-03/2025		
4	Insulator Panto Mtg.	29810127	8	MIL	02-2025, 03-2025, 04-2025		
	•	•	MIDDLE RO	OF COMPONENT			
5	High Voltage Bushing	29731021	1	ELECTRANEX	EIPL-5990-01-25		
6	Voltage Transformer	29695028	1	CG POWER & INDUSTRIAL	243372-2024		
7	Vacuum Circuit Breaker	25712202	1	Autometers	AALN/04/2025/013/VCBA/013		
8	Insulator Roof line	29810139	9	MIL	02-2025, 02-2025		
9	Harmonic Filter	29650033	1	Sunshine Industries	1339-12/2024	AS Per PO/IRS Conditions	
10	Earth Switch	29700073	1	Patra & Chanda	284-09/2024		
11	Surge Arrester	29750052	2	CG POWER & INDUSTRIAL	57369-2024, 57371-2024		
	T						
			Air B	rake Components		_	
12	Air Compressor (A,B)	29511008	2	ELGI	EXGS 923606 A, EYLS 925157 B	_	
13	Air Dryer	29162051	1	TRIDENT	LD2-05-1878-25		
14	Babby compressor	25513000	1	CEC	RB 5015-02-25		
15	Air Brake Panel	29180016	1	FAIVELEY	FEB 25-69-WAG 9-3980		
16	Contoller (A,B)	29180016	2	FAIVELEY	N 24-070 A, N 24-061 B		
17	Breakup Valve	29180016	2	FAIVELEY			
18	wiper motor	29162026	4	AUTO INDUSTRY			

PLW/PTA

ELECTRIC LOCO HISTORY SHEET (ECS)

ELECTRIC LOCO NO: 42043 LIST OF ITEMS FITTED BY ECS

RLY: NER

SHED: SYHE

PROPULSION SYSTEM: BHEL

SN		ITEM PL NO.	TEM PL NO. ITEM SR. NO CAB-1/CAB-2			
1	LED Based Flasher Light Cab I & II	29612937	26803	26729	MAKE/SUPPLIER MATSUSHI P.TECH	
2	Led Marker Light Cab I & II	29612925	104422/10445/10443/10444		SIRVEEN	
3	Cab Heater Cab I & II	29170011	2804	2797	TOPGRIP	
	Crew Fan Cab I & II	29470080	RT 07740125/0781012	25/07780125/07830125	ROTO TECH	
	Master Controller Cab I	20222245		38	NOTO ILON	
6	Master Controller Cab II	29860015		46	WOAMA	
7	Complete Panel A Cab I & II	29178265	KT-111	KT-1463	KONTACT	
	Complete Panel C Cab I & II	29170539	KT-1249	KT-1247	KONTACT/BHEL	
	Complete Panel D Cab I & II	29178265	KT-117			
	Complete Cubicle- F Panel Cab I & II	29178162		VSCF2025B004		
	Speed Ind.& Rec. System	29200040	M-2501528/S-2505042		VSONS AAL	
	Battery (Ni- Cd)	29680025	B-183		HBL	
13	Set of Harnessed Cable Complete	29600420				
14	Transformer Oil Pressure Sensor (Cab-1) (Pressure Sensor Oil Circuit Transformer)	29500047	1958 Feb25	2319 Mar25	POLYCAB	
	Transformer Oil Pressure Sensor (Cab-2)		2293 Mar25	2275 Mar25	BG INDUSTRIES	
16	Transformer Oil Temperature Sensor (Cab-1) (Temperature Sensor Oil Circuit Transformer)	29500035	BG/TFP/8959 Aug-24		BG INDUSTRIES	
	Transformer Oil Temperature Sensor (Cab-2)		BG/TFP/8953 Aug-24			
	Roof mounted Air Conditioner I	00044000	KKI/HVAC/CLW/2900			
	Roof mounted Air Conditioner II	29811028	KKI/HVAC/CLW/2902		KKI	
20	DPWCS (DDU)		1451	1452	LOTUS	

SSE/JE/Roof &U/F

SSE/JE/Machine Room

SSE/JE/Harness

			OTIVE WORKS, PATIAI 42043/NER/SYHE/1/		1	
S.No.	Equipment	PL No.		t Serial No.	Ma	ke
1	Complete Shell Assembly with piping	29171027		71, 06/25	Chandra Udy b g	
2	Side Buffer Assly Both Side Cab I		Not visible, 01/23	50, 05/23	NKII	AEU
	Side Buffer Assly Both Side Cab II	29130050	471, 02/25 253, 02/25		AEU	AEU
4	CBC Cab I & II	29130037	143, 11/24	00063, 08/24	FASP	NNFP
5	Hand Brake	2525657		3-4/25	Mechwel	
3	Hallu Blake	29045034	1003.	7 4/23		931 41110
6	Set of Secondry Helical Spring	29043034			Frontier	
7	Battery Boxes (both side)	29680013	172, 02/25	149, 03/25	BHARTIA BRIGHT	BHARTIA BRIGHT
8	Traction Bar Bogie I		8942,	05/25	KN	Л
9	Traction Bar Bogie II		8920,	04/25	KN	Л
10	Centre Pivot Housing in Shell Bogie I side	29100057	466,	02/25	AN	IL
11	Centre Pivot Housing in Shell Bogie II side	29100037	441,	02/25	AN	IL
12	Elastic Ring in Front in Shell Bogie I side	20100010	05/32	, 08/24	SSI	PL
13	Elastic Ring in Front in Shell Bogie II side	29100010	05/16	, 12/24	SSI	PL
14	Main Transformer	29731008 for WAG 9 29731057 for WAP-7	MIPL-65-03-2	25-0006, 2025	. Mah	nati
15	Oil Cooling Radiator I	20470024	03/25, P0	325RC2809 ,	FINE AUTOMOTIVE	
16	Oil Cooling Radiator II	29470031	03/25, PO	325RC2818	FINE AUTOMOTIVE	
17	Main Compressor I with Motor	20544000	EYLS 925157, 03/25		ELGi	
18	Main Compressor II with Motor	29511008	FX65 923606, 10/24		ELG	Gi
19	Transformer Oil Cooling Pump I	The state of the s	2412DC4047, 2024		FLOV	VOIL
20	Transformer Oil Cooling Pump II		2412DC4087, 2024		· FLOV	VOIL &
21	Oil Cooling Blower OCB I		03/25, AC-600			CCEL
22	Oil Cooling Blower OCB II	29470043	03/25,AC-60412 LHP100162 1527		ACC	
23	TM Blower I		02/25, 24P6794/14 , 24P6794AF14		SAI	
		29440075		09 , 24P6794AF09	SAI	
24	TM Blower II				SAMAL *	
25	Machine Room Blower I	29440105		01,MF42/D 6248	SAMAL	
26	Machine Room Blower II			74,MF42/D 6221		
27	Machine Room Scavenging Blower I	29440129		Л-25.03.74	GT	
28	Machine Room Scavenging Blower II		-	Л-25.03.68	GT	
29	TM Scavenging Blower Motor I	29440117		/42, 24P8000AF42	SAI	
30	TM Scavenging Blower Motor II			/44, 24P8000AF44	SAI	NI
31	Traction Convertor I			9 (PLW-15A)		
32	Traction Convertor II		, ,	0(PLW-15B)		
33	Vehicle Control Unit I	29741075		304680018	ВН	EL
34	Vehicle Control Unit II			0304750018		
35	Aux. Converter Box I (BUR 1)			1, 1451	_	
36	Aux. Converter Box 2 (BUR 2 + 3)	20171100		1, 1451 /1020/04/20 § 5	KAYS	ONS
37	Axillary Control Cubical HB-1 Axillary Control Cubical HB-2	29171180 29171192)25/C/0178/751	HIND re	
				B-1/25020986	C	
39 40	Complete Control Cubicle SB-1 Complete Control Cubicle SB-2	29171209 29171210		B-2/2502/106	KAPTR	
41	Filter Cubical (FB) (COMPLETE FILTER CUBICLES)	29480140		25/D/0274/663	· HIND re	
42	Driver Seats	29171131	4/25- 104.	227, 81, 187	TARU	DEEP
43	Transformer oil steel pipes	29230044		IT PIPES		
44	Conservator Tank Breather	29731057		,24-8223,	You	gya
45	Ballast Assembly (only for WAG-9)	29170163		,46,92	AK	

NAME SELLAS

NAME ALLICIT UPPAL JE/LAS/UF NAME....Perunday. N ang

Issue No.: 05 Effective Date: July-2023 DOC NO: F/LAS/Electric Loco CHECK SHEET (Ref: WI/LAS/Elect/01, 02, 03 & 04 & QPL/LAS/Elect. Loco)
Page 1 of 1

पटियाला रेलइंजन कारखाना, पटियाला PATIALA LOCOMOTIVE WORKS, PATIALA ELECTRIC LOCO CHECK SHEET

LOCO NO: 42043

Rly: NER

Shed: SYHE

S. No.	ITEM TO BE CHECKED	Specified Value	(Observe	d Valu	ie
1.1	Check proper Fitment of Hotel Load Converter & its output contactor.	OK		-0	NA	,
1.2	Check proper Fitment of MR Blower 1 & 2, MR Scavenging Blower 1 & 2, TM Blower 1 & 2, TMB Scavenging Blower 1 & 2. TM scavenging blower 1 & 2 & Oil Cooling unit.	OK		CL		
1.3	Check proper of Fitment of oil cooling unit (OCU).	OK		0	<u>JL</u> J2	
1.4	Check proper Fitment of HB 1 & 2 and its respected lower part on its position.	OK		Ö	72	
1.5	Check proper Fitment of FB panel on its position.	OK			12	
1.6	Check proper Fitment of assembled SB1 & SB2 panel.	OK		0	12	
1.7	Check proper Fitment of Auxiliary converter 1, 2 & 3-(BUR-1, 2 & 3).	OK		0	2	
1.8	Check proper Fitment of Traction converter 1 & 2 (SR-1 & 2).	OK		0	12	
1.9	Check proper fitment, torquing & Locking of Main Transformer bolt.	OK		0	R	
1.10	Check proper fitment of Main compressor both side with the compressor safety wire rope.	OK			12	
1.11	Check proper resting of Secondary Helical Springs between Bogie & Shell body.	OK			1/L	
1.12	Check proper fitment of Bogie Body Safety Chains.	OK			1/2	
1.13	Check proper fitment of Cow catcher.	OK	OK			
1.14	Check coolant level in SR 1 & 2 Expansion Tank.	OK	OK			
1.15	Check Transformer Oil Level in both conservators Tank (Breather Tank).	OK	OR			
1.16	Check proper fitment and maintain required gaps from Loco Shell Body of all metallic pipes to avoid any damage during online working of Locomotives.	OK	0/2			
1.17	Check proper fitment of both battery box.	OK	al			
1.18	Check for any gap between Main Transformer mounting base & Loco Shell.	OK	0/2			
1.19	Check proper fitment of Push Pull rod its bolt torquing and fitment of fixing cable. As per Drg No 1209-01-113-001	OK	0/4			
1.20	Secondary Vertical and Lateral Clearance on leveled track at the time of Loco Dispatch.		C	AB-1	(CAB-2
	ELRS/TC/ 0082 (Rev 1) dated 17.09.2015	Vertical-Std	LP	ALP	LP	ALP
		:35-60 mm	46	45	48	To
		Lateral Std-	1		'	-
		45-50 mm	42	58	60	43
1.21	Buffer height: Range (1090, +15,-5)	1085-1105		L	S	R/S
1.21	Drg No IB031-02002.	mm	FRONT	1	72	1093
			REAR	10		
			REAR		15	1093
1.22	Buffer Length: Range (641 mm + 3 to 10 mm with buffer face)	641 mm		L	-	R/S
	Drg No-SK.DL-3430.		FRONT	0		645
			REAR	65	O	645
1.23	Height of Rail Guard. (114 mm + 5 mm,-12 mm).	114 mm + 5	- 10	L	S	R/S
1.23	As per RDSO Pamphlet Important Bogie Clearances of Electric Locomotives.	mm,-12 mm	FRONT	110	7	114
			REAR	118	District Control	118
1.24	CBC Height: Range (1090, +15,-5) Drg No- IB031-02002.	1090, +15 -5 mm	FRONT REAR:			

(Signature of SSE/Elect. Loco)

NAME (HUBBAN SHIRM

DATE 30.06.25

(Signature of /JE/Elect Loco)

NAME ROUNDE MEENS

DATE 30.06.25

(Signature of JE/UF)

NAME ANICT UPPAL

DATE 30 -66-2025

Loco No. 42043

1. BOGIE FRAME:

BOGIE	FRAME NO	Make	PL No.	PO No. & dt.	Warranty Period
FRONT	SL-2871	ACPL	29101104	102222	As per PO/IRS
REAR	SL-451	ECBT	29101104	102079	conditions

2. Hydraulic Dampers (PL No.29040012) Make: KNORR / KNORR

3. AXLES:

AXLE POSITION NO	1	2	3	4	5	6
MAKE/	PLW	PLW	PLW	PLW	PLW	PLW
S.NO	28643	28753	28740	28983	28646	28662
Ultrasonic Testing	OK	OK	OK	OK	OK	OK

4. WHEEL DISCS NO. AND TYPE & BULL GEAR

AXLE POSITION NO	1	2	3	4	5	6
GEAR END	EV63-065	EV70-037	EV38-004	EQB3-055	EV72-044	EV38-063
Make	IMPORTED	IMPORTED	IMPORTED	IMPORTED	IMPORTED	IMPORTED
FREE END	EQA8-090	EV44-060	EV34-010	EQ53-027	EV72-006	EV34-060
Make	IMPORTED	IMPORTED	IMPORTED	IMPORTED	IMPORTED	IMPORTED
Bull Gear No.	25-B-15172	EL-63	25-B-12193	25-B-9131	25-B-9155	25-B-15137
Bull Gear Make	KPCL	ELICON	KPCL	KPCL	KPCL	KPCL

5. AXLE ROLLER BEARING (CRU) (PL No. 29010020, Warranty: As per PO/IRS conditions)

	AXLE POSITION NO	1	2	3	4	5	6
Gear	MAKE	FAG	FAG	FAG	FAG	FAG	FAG
End	PO NO. & dt	02312	02312	02312	02312	02312	02312
Free	MAKE	FAG	FAG	FAG	FAG	FAG	FAG
End	PO NO. & dt	02312	02312	02312	02312	02312	02312

6. WHEEL DISC PRESSING PRESSURE IN KN: (SPECIFIED 80-105 T)

AXLE POSITION NO	1	2	3	4	5	6
BULL GEAR END	102 T	788 KN	895 KN	983 KN	881 KN	985 KN
FREE END	101 T	86 T	795 KN	820 KN	930 KN	963 KN

Loco No. 42043

7. DIAMETER AFTER PROFILE TURNING: SPECIFIED 1092 + .5 mm - 0 mm

AXLE POSITION NO	1	2	3	4	5	6
DIA IN mm GE	1092.5	1092.5	1092.5	1092.4	1092.5	1092.5
DIA IN mm FE	1092.5	1092.5	1092.5	1092.4	1092.5	1092.5
WHEEL PROFILE GAUGE (1596±0.5mm)	OK	OK	OK	OK	OK	OK

8. SUSPENSION TUBE & ITS TAPER ROLLER BEARING:

AXLE POSITION	NO	1	2	3	4	5	6
S.T. PL 29100288	MAKE	IN	IN	IN	IN	IN	IN
GE Brg. PL 29030110	MAKE	FAG	FAG	FAG	FAG	FAG	FAG
FE Brg. PL 29030110	MAKE	FAG	FAG	FAG	FAG	FAG	FAG

9. GEAR CASE (PL No. 29030018) & BACKLASH:

AXLE POSITION NO	1	2	3	4	5	6
MAKE	KPE	PEPL	KPE	EEE	KPE	KPE
BACKLASH (0.254 – 0.458mm)	0.350	0.300	0.400	0.350	0.310	0.300

10 A/BOX TO BOGIE FRAME LATERAL CLEARANCES (SPECIFIED 15.0 to 19.0mm):

AXLE POSITION NO	1	2	3	4	5	6
RIGHT SIDE	16.35	17.42	16.52	15.61	17.62	15.81
LEFT SIDE	16.82	17.98	16.18	15.46	18.05	15.91

11. TRACTION MOTOR: (PL No.29940606, Warranty: As per PO/IRS conditions)


AXLE POSITION NO	MAKE	PO No. & Date	S. NO.		
1	SAINI	102034	210962411		
2	SAINI	102034	211142411		
3	SAINI	102034	210972411		
4	SAINI	102034	211162411		
5	SAINI	102034	211172411		
6	SAINI	102034	211212411		

JE/SSE/ Bogie Shop

Date and TimeDt:28/5/2025 Tm:10:15	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC61 *

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm


Observation/Remarks (If Any):

Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:10:15	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)

.....



 Data Setup

 Gain: 38.0 dB
 Gate 1 (Status): OFF

 RANGE: 2500.00mm
 Gate 2 (Status): OFF

 MTL VEL: 5920 M/S
 Gate 1(Echo height): 0 %

 REJECT: 12 %
 Gate 1(Beam Path): 0.00mm

PROBE ZERO: 8.78us

Gate 1(Depth): 0.00mm

MODE: SINGLE

PROBE ANGLE: 0.0DEG

Gate 2(Echo height):

Gate 2(Beam Path): mm

THICK: 100.00mm

Gate 2(Surface Distance): 1

Gate 2(Surface Distance): mm

Gate 1(Surface Distance): 0.00mm

Gate 2(Depth): mm


Observation/Remarks (If Any):

DELAY: 0.06mm

Frame No: ASC62 *

Date and TimeDt:28/5/2025 Tm:10:15	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)



Data Setup
Gain: 39.0 dB
Gate 1 (Status): OFF
RANGE: 2500.00mm
Gate 2 (Status): OFF
MTL VEL: 5920 M/S
Gate 1(Echo height): 0 %
Gate 1(Beam Path): 0.00mm
DELAY: 0.06mm
Gate 1(Surface Distance): 0.00mm
PROBE ZERO: 8.78us
Gate 2(Echo height):
Gate 2(Echo height):

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Observation/Remarks (If Any):

Frame No: ASC63 *

Date and TimeDt:28/5/2025 Tm:10:15	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC64 *

(A-Scan)



Data Setup Gain: 39.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:16

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28643


Operator Name/Code: RAMVEER MEENA

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC65 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:16

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel...: WAG9 Axle/wheel No:28643

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC66 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:16

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code: RAMVEER MEENA


Defect Location GE

Test Results (Pass/Enil/other):

Test Results (Pass/Fail/other):

If other, then Remarks.....Frame No: ASC67 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:28/5/2025 Tm:10:16 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28643


Operator Name/Code : RAMVEER MEENA

Defect Location GE

Test Results (Pass/Fail/other): If other, then Remarks.....

Frame No: ASC68 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:17
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC69 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:17

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC70 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......Dt:28/5/2025 Tm:10:17

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code : RAMVEER MEENA


Defect Location: GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC71 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:28/5/2025 Tm:10:17 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28643 Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC72 *

(A-Scan)



Data Setup

RANGE: 1000.00mm

Gain: 49.0 dB Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:24

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC73 *

(A-Scan)



Data Setup

Gain: 48.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:28/5/2025 Tm:10:24

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel...: WAG9 Axle/wheel No:28643

Operator Name/Code: RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC74 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8,78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:28/5/2025 Tm:10:24 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28643 Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC75 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm THICK: 100.00mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:10:25

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28643

Operator Name/Code: RAMVEER MEENA


Defect Location: FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC76 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):


PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:10:25	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC77 *	

(A-Scan)




Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:10:25	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location: FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC78 *	

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Observation/Remarks (If Any):

THICK: 100.00mm

Date and TimeDt:28/5/2025 Tm:10:25	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28643
Operator Name/Code : RAMVEER MEENA	
Defect Location: FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC79 *	


(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

(A-Scan)



 Data Setup

 Gain: 38.0 dB
 Gate 1 (Status): OFF

 RANGE: 2500.00mm
 Gate 2 (Status): OFF

 MTL VEL: 5920 M/S
 Gate 1(Echo height): 0 %

 REJECT: 12 %
 Gate 1(Beam Path): 0.00mm

 DELAY: 0.06mm
 Gate 1(Surface Distance): 0.00mm

 PROBE ZERO: 8.78us
 Gate 1(Depth): 0.00mm

PROBE ZERO: 8.78us

Gate 1(Depth): 0.00mm

MODE: SINGLE

PROBE ANGLE: 0.0DEG

Gate 2(Beam Path): mm

THICK: 100.00mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:26/5/2025 Tm:10:58

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code: RAMVEER MEENA


Defect Location: GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC81 *

(A-Scan)



Data Setup Gain: 40.0 dB

RANGE: 2500.00mm

MTL VEL: 5920 M/S

REJECT: 12 % DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1 (Status): OFF

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):


Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

(A-Scan)

Frame No: ASC82 *



Data Setup
Gain: 40.0 dB
Gate 1 (Status): OFF
RANGE: 2500.00mm
Gate 2 (Status): OFF
MTL VEL: 5920 M/S
GATE 1 (Echo height): 0 %
GATE 1 (Beam Path): 0.00mm
DELAY: 0.06mm
GATE 1 (Surface Distance): 0.00mm
PROBE ZERO: 8.78us
GATE 1 (Depth): 0.00mm
GATE 2 (Echo height):


PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

(A-Scan)


Frame No: ASC83 *



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:26/5/2025 Tm:10:58	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28753
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC84 *	

(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Gate Zibeptiij. iiii

Date and Time......:Dt:26/5/2025 Tm:11:1

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop...: BS PLW

Type of Axle/wheel...: WAG9 Axle/wheel No:28753


Operator Name/Code: RAMVEER MEENA

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC85 *

(A-Scan)



Data Setup

Gain: 50.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:1 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC86 *

(A-Scan)



Data Setup

Gain: 50.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:26/5/2025 Tm:11:1

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel...: WAG9 Axle/wheel No:28753


Operator Name/Code: RAMVEER MEENA

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC87 *

(A-Scan)



Data Setup

Gain: 50.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:26/5/2025 Tm:11:1

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code: RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC88 *

(A-Scan)



Data Setup

Gain: 47.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Surface Distance): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:2
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC89 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:2 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753 Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC90 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us

Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:26/5/2025 Tm:11:3
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC91 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:26/5/2025 Tm:11:3
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC92 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:26/5/2025 Tm:11:7
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC93 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:8
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC94 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:8

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location: FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC95 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:8

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28753

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC96 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:26/5/2025 Tm:11:8	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28753
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC97 *

(A-Scan)




Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:9 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28753 Operator Name/Code : RAMVEER MEENA Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks..... Frame No: ASC98 *

(A-Scan)



Data Setup

Gain: 40.0 dB RANGE: 2500.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1 (Status): OFF

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Date and Time......Dt:26/5/2025 Tm:11:9 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28753 Operator Name/Code : RAMVEER MEENA Defect Location FE

Test Results (Pass/Fail/other): If other, then Remarks.....

Frame No: ASC99 *

(A-Scan)



Data Setup

Gain: 40.0 dB

RANGE: 2500.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1 (Status): OFF

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:26/5/2025 Tm:11:9	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28753
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC100 *

(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm


Date and TimeDt:27/5/2025 1m:12:55	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	

If other, then Remarks.....

Frame No: ASC161 *

Observation/Remarks (If Any):


(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:55	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC162 *	

(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and Time.......:Dt:27/5/2025 Tm:12:56

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop.....: BS PLW

Type of Axle/wheel.....: WAG9 Axle/wheel No:28740

Operator Name/Code: RAMYEER MEENA


Defect Location: GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC163 *

(A-Scan)



Data Setup

Gain: 41.0 dB

RANGE: 2500.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1 (Status): OFF

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:56	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other then Bemarks	

Frame No: ASC164 *

(A-Scan)



Data Setup Gain: 44.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:56 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28740


Operator Name/Code : RAMVEER MEENA

Defect Location GE

Test Results (Pass/Fail/other): If other, then Remarks.....

Frame No: ASC165 *

(A-Scan)



Data Setup

Gain: 46.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 %

Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:57 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28740 Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC166 *

(A-Scan)



Data Setup

REJECT: 12 %

Gain: 47.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:27/5/2025 Tm:12:57

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code: RAMVEER MEENA


Defect Location: GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC167 *

(A-Scan)



Data Setup

Gain: 47.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:57

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC168 *

(A-Scan)



Data Setup

Gain: 47.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:57 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28740


Operator Name/Code : RAMVEER MEENA Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC169 *

(A-Scan)



Data Setup

Gain: 53.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:58 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC170 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......Dt:27/5/2025 Tm:12:58
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC171 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:58

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC172 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:13:3
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC173 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC174 *

(A-Scan)



Data Setup

Gain: 53.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:13:3 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28740


Operator Name/Code : RAMVEER MEENA Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC175 *

(A-Scan)



Data Setup

Gain: 53.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:13:3 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28740

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC176 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Gate 1 (Status): PLOGIC

Date and TimeDt:27/5/2025 Tm:13:4	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC177 *

Observation/Remarks (If Any):


(A-Scan)



Data Setup Gain: 43.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

(A-Scan)

Frame No: ASC178 *



Data Setup
Gain: 43.0 dB
RANGE: 2500.00mm
MTL VEL: 5920 M/S
REJECT: 12 %
DELAY: 0.06mm
PROBE ZERO: 8.78us
MODE: SINGLE

PROBE ANGLE: 0.0DEG

Gate 1 (Status): OFF
Gate 2 (Status): OFF

Gate 1(Echo height): 0 % Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:27/5/2025 1m:13:4	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect Location: FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC179 *

(A-Scan)




Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and Time:Dt:27/5/2025 Tm:13:4	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28740
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail <u>/other):</u>	

If other, then Remarks.....

Frame No: ASC180 *

(A-Scan)



Data Setup
Gain: 40.0 dB
RANGE: 2500.00mm
MTL VEL: 5920 M/S
REJECT: 12 %
DELAY: 0.06mm
PROBE ZERO: 8.78us
MODE: SINGLE

PROBE ANGLE: 0.0DEG THICK: 100.00mm Gate 1 (Status): OFF
Gate 2 (Status): OFF
Gate 1(Echo height): 0 %
Gate 1(Beam Path): 0.00mm
Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):


Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:9:38	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28983
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC01 *	

(A-Scan)




Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:9:38	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28983
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC02 *


(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Frame No: ASC03 *

(A-Scan)



Data Setup Gain: 38.0 dB

RANGE: 2500.00mm

MTL VEL: 5920 M/S REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 0.0DEG

THICK: 100.00mm

Gate 1 (Status): OFF

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Axle/wheel No:28983

Frame No: ASC04 *

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:9:39

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code: RAMVEER MEENA


Defend to the series of the se

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC05 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Date and Time......Dt:28/5/2025 Tm:9:39 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28983 Operator Name/Code : RAMVEER MEENA

Defect Location GE

Test Results (Pass/Fail/other): If other, then Remarks.....

Frame No: ASC06 *

(A-Scan)



Data Setup

Gain: 45.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

Gate 2(Beam Path): mm THICK: 100.00mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Observation/Remarks (If Any):

PROBE ANGLE: 10.0DEG

Date and Time......:Dt:28/5/2025 Tm:9:40

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code: RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC07 *

(A-Scan)



Data Setup

Gain: 45.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......Dt:28/5/2025 Tm:9:40

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983


Operator Name/Code: RAMVEER MEENA

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC08 *

(A-Scan)



Data Setup

Gain: 45.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:9:40
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC09 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:9:40
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC10 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:28/5/2025 Tm:9:41
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC11 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:9:41 UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC12 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:28/5/2025 Tm:9:46 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC13 *

(A-Scan)



Data Setup

Gain: 52.0 dB

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Gate 1 (Status): PLOGIC

Date and Time......Dt:28/5/2025 Tm:9:46
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: <u>BS PLW</u>

Type of Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC14 *

(A-Scan)



Data Setup

Gain: 52.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:28/5/2025 Tm:9:46
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28983

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC15 *

(A-Scan)



Data Setup

Gain: 52.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Date and Time......Dt:28/5/2025 Tm:9:46 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28983 Operator Name/Code : RAMVEER MEENA

Defect Location FE Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC16 *

(A-Scan)



Data Setup

Gain: 52.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 17.5DEG

Gate 2(Beam Path): mm THICK: 100.00mm

Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:9:47	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28983
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC17 *

Observation/Remarks (If Any):


(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:28/5/2025 Tm:9:47	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28983
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other than Damarka	

(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm


Odle Zibepini, min

Observation/Remarks (If Any):

Frame No: ASC18 *

(A-Scan)

Frame No: ASC19 *



 Data Setup

 Gain: 40.0 dB
 Gat

 RANGE: 2500.00mm
 Gat

 MTL VEL: 5920 M/S
 Gat

 REJECT: 12 %
 Gat

 DELAY: 0.06mm
 Gat

 PROBE ZERO: 8.78us
 Gat

 MODE: SINGLE
 Gat

 PROBE ANGLE: 0.0DEG
 Gat

Gate 1 (Status): OFF
Gate 2 (Status): OFF
Gate 1(Echo height): 0 %
Gate 1(Beam Path): 0.00mm
Gate 1(Surface Distance): 0.00mm
Gate 1(Depth): 0.00mm
Gate 2(Echo height):
Gate 2(Beam Path): mm
Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Observation/Remarks (If Any):

THICK: 100.00mm

Date and TimeDt:28/5/2025 Tm:9:47	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28983
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other then Remarks	

(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Observation/Remarks (If Any):

Frame No: ASC20 *

Date and TimeDt:27/5/2025 Tm:10:1	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Observation/Remarks (If Any):

Frame No: ASC41 *

Date and TimeDt:27/5/2025 Tm:10:1	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC42 *	


(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:10:1	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC43 *	

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

Gate 2(Depth): mm


Gate 2(Surface Distance): mm

Observation/Remarks (If Any):

THICK: 100.00mm

Date and TimeDt:27/5/2025 Tm:10:1	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC44 *	

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm


Date and Time......Dt:27/5/2025 Tm:10:2 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28646 Operator Name/Code : RAMVEER MEENA

Defect Location GE Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC45 *

(A-Scan)



Data Setup

Gain: 51.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm THICK: 100.00mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:27/5/2025 Tm:10:3

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC46 *

(A-Scan)



Data Setup

Gain: 46.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:3 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC47 *

(A-Scan)



Data Setup

Gain: 46.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:10:3

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code: RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC48 *

(A-Scan)



Data Setup

Gain: 47.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

Test Results (Pass/Fail/other):

If other, then Remarks......Frame No: ASC49 *

(A-Scan)



Data Setup

Gain: 48.0 dB Gate 1 (Status): PLOGIC

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm
PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):
PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:4 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28646


Operator Name/Code : RAMVEER MEENA Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC50 *

(A-Scan)



Data Setup

Gain: 48.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:4

UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC51 *

(A-Scan)



Data Setup

Gain: 48.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:4 UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC52 *

(A-Scan)



Data Setup

Gain: 48.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:10:9 UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC53 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Gate 1 (Status): PLOGIC

Date and Time.......:Dt:27/5/2025 Tm:10:9
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC54 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:9
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28646

Operator Name/Code : RAMVEER MEENA


Defect Location FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC55 *

(A-Scan)



Data Setup

Gain: 50.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:10:9 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28646


Operator Name/Code : RAMVEER MEENA

Defect Location FE

Test Results (Pass/Fail/other): If other, then Remarks.....

Frame No: ASC56 *

(A-Scan)



Data Setup

Gain: 50.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S

Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm


PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:10:10	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)



Data Setup
Gain: 38.0 dB Gate 1 (Status): OFF
RANGE: 2500.00mm Gate 2 (Status): OFF
MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm
DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm
PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm
MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm


Gate 2(Depth): mm

Observation/Remarks (If Any):

Frame No: ASC57 *

Date and TimeDt:27/5/2025 Tm:10:10	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other then Remarks	

(A-Scan)



Data Setup Gain: 39.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Observation/Remarks (If Any):

Frame No: ASC58 *

Date and TimeDt:27/5/2025 Tm:10:10	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

Frame No: ASC59 *


(A-Scan)



Data Setup Gain: 39.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:10:10	
UFD Model: Arya 1(R) Sr No:AA0362-4220	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28646
Operator Name/Code : RAMVEER MEENA	
Defect Location FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC60 *	

(A-Scan)




Data Setup Gain: 39.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:40	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC141 *	


(A-Scan)



Data Setup Gain: 41.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:41	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC142 *	


(A-Scan)



Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:41	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect LocationGE	
Test Results (Pass/Fail/other):	
If other, then Remarks	
Frame No: ASC143 *	

(A-Scan)




Data Setup Gain: 40.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:2//5/2025 Tm:12:41	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect Location GE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)



Data Setup Gain: 37.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

Gate 2(Depth): mm

Gate 2(Surface Distance): mm

Observation/Remarks (If Any):

THICK: 100.00mm

Frame No: ASC144 *


Date and Time.......:Dt:27/5/2025 Tm:12:42
UFD Model: Arya 1(R) Sr No:AA0362-4220
Railway/Workshop....: BS PLW
Type of Axle/wheel....: WAG9 Axle/wheel No:28662
Operator Name/Code: RAMVEER MEENA

Defect Location GE
Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC145 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:42
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC146 *

(A-Scan)



Data Setup

Gain: 49.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 10.0DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Date and Time......Dt:27/5/2025 Tm:12:42 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28662 Operator Name/Code : RAMVEER MEENA

Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks..... Frame No: ASC147 *

(A-Scan)



Data Setup

Gain: 48.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC148 *

(A-Scan)



Data Setup

Gain: 48.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 10.0DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:43
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC149 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:43 UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC150 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:43
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC151 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time.......:Dt:27/5/2025 Tm:12:43
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA


Defect Location GE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC152 *

(A-Scan)



Data Setup

Gain: 53.0 dB

RANGE: 1000.00mm

MTL VEL: 5920 M/S

REJECT: 12 %

DELAY: 0.06mm

PROBE ZERO: 8.78us

MODE: SINGLE

PROBE ANGLE: 17.5DEG

THICK: 100.00mm

Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF

Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm

Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:48

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code: RAMVEER MEENA


Defect Location: FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC153 *

(A-Scan)



Data Setup

Gain: 49.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mr

EJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......Dt:27/5/2025 Tm:12:48
UFD Model: <u>Arya 1(R)</u> Sr No:<u>AA0362-422</u>0
Railway/Workshop.....: <u>BS PLW</u>

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code : RAMVEER MEENA

Operation MainerCode . COMMYLLIN MILLING


Defect Location FE

Test Results (Pass/Fail/other):

Test Results (Pass/Fail/other):

If other, then Remarks......Frame No: ASC154 *

(A-Scan)



Data Setup

Gain: 51.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):

PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Date and Time......Dt:27/5/2025 Tm:12:49 UFD Model: Arya 1(R) Sr No:AA0362-4220 Railway/Workshop.....: BS PLW Type of Axle/wheel....: WAG9 Axle/wheel No:28662 Operator Name/Code : RAMVEER MEENA

Defect Location FE Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC155 *

(A-Scan)



Data Setup

RANGE: 1000.00mm

Gain: 51.0 dB Gate 1 (Status): PLOGIC

Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 %

REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and Time......:Dt:27/5/2025 Tm:12:49

UFD Model: Arya 1(R) Sr No:AA0362-4220

Railway/Workshop....: BS PLW

Type of Axle/wheel....: WAG9 Axle/wheel No:28662

Operator Name/Code: RAMVEER MEENA


Defect Location: FE

Test Results (Pass/Fail/other):

If other, then Remarks.....

Frame No: ASC156 *

(A-Scan)



Data Setup

Gain: 51.0 dB Gate 1 (Status): PLOGIC

RANGE: 1000.00mm Gate 2 (Status): OFF

MTL VEL: 5920 M/S Gate 1(Echo height): 0 %
REJECT: 12 % Gate 1(Beam Path): 0.00mm

DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm

PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm

MODE: SINGLE Gate 2(Echo height):


PROBE ANGLE: 17.5DEG Gate 2(Beam Path): mm

THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm

(A-Scan)

Frame No: ASC157 *



Data Setup
Gain: 38.0 dB
RANGE: 2500.00mm
MTL VEL: 5920 M/S
REJECT: 12 %
DELAY: 0.06mm
PROBE ZERO: 8.78us
MODE: SINGLE

PROBE ANGLE: 0.0DEG

Gate 1 (Status): OFF
Gate 2 (Status): OFF
Gate 1(Echo height): 0 %

Gate 1(Beam Path): 0.00mm

Gate 1(Surface Distance): 0.00mm

Gate 1(Depth): 0.00mm

Gate 2(Echo height):

Gate 2(Beam Path): mm


Gate 2(Surface Distance): mm

Gate 2(Depth): mm

Date and TimeDt:27/5/2025 Tm:12:49	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail/other):	
If other than Domarka	

(A-Scan)

·



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Observation/Remarks (If Any):

Frame No: ASC158 *

Date and TimeDt:27/5/2025 Tm:12:49	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect Location: FE	
Test Results (Pass/Fail/other):	
If other, then Remarks	

(A-Scan)

.....



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm THICK: 100.00mm Gate 2(Surface Distance): mm

Gate 2(Depth): mm


Observation/Remarks (If Any):

Frame No: ASC159 *

Date and TimeDt:27/5/2025 Tm:12:49	
UFD Model: <u>Arya 1(R)</u> Sr No: <u>AA0362-422</u> 0	
Railway/Workshop: BS PLW	
Type of Axle/wheel: WAG9	Axle/wheel No:28662
Operator Name/Code : RAMVEER MEENA	
Defect LocationFE	
Test Results (Pass/Fail <u>/other):</u>	
If other, then Remarks	

Frame No: ASC160 *

(A-Scan)



Data Setup Gain: 38.0 dB Gate 1 (Status): OFF RANGE: 2500.00mm Gate 2 (Status): OFF MTL VEL: 5920 M/S Gate 1(Echo height): 0 % REJECT: 12 % Gate 1(Beam Path): 0.00mm DELAY: 0.06mm Gate 1(Surface Distance): 0.00mm PROBE ZERO: 8.78us Gate 1(Depth): 0.00mm MODE: SINGLE Gate 2(Echo height): PROBE ANGLE: 0.0DEG Gate 2(Beam Path): mm

Gate 2(Depth): mm

Gate 2(Surface Distance): mm

Observation/Remarks (If Any):

THICK: 100.00mm

TOP 12 COSTLIEST ITEMS OF WAG9HC LOCO WITH WARRANTY CONDITIONS AS PER TENDERS

S No	PL No	DESCRIPTION	Warranty Period	
1	29741075	IGBT BASED 3-PHASE DRIVE PROPULSION EQUIPMENT	60 months after commissioning or 72 months from date of supply whichever earlier as per special conditions given by CLW	
2	29731057	MAIN TRANSFORMER 7775 KVA TYPE LOT 7500 FOR WAP7 3- PHASE ELECTRIC LOCOMOTIVE TO CLW SPECN NO.CLW/ES/3/0660/C	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.	
3	29171064	COMPLETE SHELL ASSLY (PIPED & PAINTED) FOR WAP-7 LOCO TO CLW SPEC. NO. CLW/MS/3/152 ALT- 8	AS PER IRS CONDITIONS-30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER.	
4	29600418	LOCOMOTIVES TO CLW SPECN. NO. CLW/ES/03/646 ALT-NIL WITH DMW REQUIREMENT OF HARNESSED	As per clause no.9 of CLW Specn. CLW/ES/3/0458 & Clause No.10 of CLW SpecnCLW/ES/3/0459. [18 months after commissioning or 20 months from date of supply for single core & 18 months after commissioning or 24 months from date of supply for multi core]	

7	29942007	3-PHASE ASYNCHRONOUS TRACTION MOTOR (RESISTANCE RING MECHANICALLY INTERLOCKED TO END PLATE DESIGN ROTOR, SCHEME-II), TYPE 6FRA-6068 FOR WAP-7 ELECTRIC LOCO WITHOUT ACTIVE SPEED SENSOR TO SPECIFICATION NO. 4TMS.096.081 ALT-2 AND STR NO. CLW/2008/3PHTM/STR/0001.	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.
6	29480140	COMPLETE FILTER CUBICLE ALONG WITH ALL EQUIPMENTS AND CABLING TO DRG./SPEC NO. [1] CLW/ES/3/0193 ALT-F OR LATEST AND CLW DRG. NO. 1209-15-143-004 ALT-10 AND PART DRG./SPEC NO AS PER ANNEXURE-A ATTACHED.	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.
5	29180016	BRAKE CONTROL SYSTEM INCLUDING DRIVER'S VIGILANCE CONTROL DEVICE TO SET LIST NO.EL29180016.	As per specification no. CLW/MS/3/001 Alt. 16 i.e. the manufacturer is required to guarantee that the brakevalves/equipment work satisfactorily for a period of five (5) years after commissioning. Any equipment/part which failsduring the guarantee period shall be replaced free of cost by the manufacturer. The replaced components shallfurther be under warranty for five (5) years from the date of their fitment and should the replaced components proveunsatisfactory in service, they shall be replaced by modified and improved components by the supplier free of cost.

8	29105146	Bogie Frame Complete for WAP-7 for 3 Phase Co Co Locomotive to CLW specification No. CLW/MS/3/Bogie/003 alt-1 and CLW Drg.No.1209.01.112-202 Alt-Nil	As per clause 16 of Spec.No.CLW/MS/3/Bogie/003 Alt-1. [60 months after commissioning or 72 months from date of supply]
9	29171192	COMPLETE AUXILIARY CUBICLE HB2 ALONG WITH ALL EQUIPMENTS AND CABLING TO CLW SPEC.NO.CLW/ES/3/0192 ALT-E OR LATEST FOR WAP7 LOCO WITH HOTEL LOAD WITH BARE CUBICLE AS PER CLW SPEC.NO.CLW/MS/3/155 ALT-NIL.	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.
10	29171210	COMPLETE CONTROL CUBICLE SB2 ALONG WITH ALL EQUIPMENTS AND CABLING (EXCLUDING CONTROL ELECTRONICS) TO CLW SPECN. NO. CLW/ES/3/0195/A ALT-H OR LATEST FOR WAP7 LOCO WITH HOTEL LOAD	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.
11	29171209	COMPLETE CONTROL CUBICLE SB1 (PUSH PULL SCHEME COMPLIANT) ALONG WITH ALL EQUIPMENTS AND CABLING (EXCLUDING CONTROL ELECTRONICS) TO CLW SPECN. NO. CLW/ES/3/0194 ALT-G OR LATEST FOR WAP7 LOCO WITH HOTEL LOAD	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.
12	29171180	COMPLETE AUXILIARY CUBICLE HB1 ALONG WITH ALL EQUIPMENTS AND CABLING TO CLW SPEC.NO.CLW/ES/3/0191 ALT-D OR LATEST FOR WAP7 LOCO WITH HOTEL LOAD WITH BARE CUBICLE AS PER CLW SPEC.NO.CLW/MS/3/155 ALT-NIL.	AS PER IRS CONDITIONS OF CONTRACT [i.e. 30 MONTHS FROM THE DATE OF SUPPLY OR 24 MONTHS FROM THE DATE OF COMMISSIONING, WHICHEVER IS EARLIER] WILL BE APPLICABLE.



भारत सरकार GOVERNMENT OF INDIA

रेल मंत्राल्य

MINISTRY OF RAILWAYS

पटियाला रेलइंजन कारखाना

PATIALA LOCOMOTIVE WORKS

Email: dyceeloco.dmw@gmail.com फैक्स/Fax No.: 0175-2397244 फोन/ Phone: 0175- 2396422 मोबाईल: 9779242310 पटियाला, 147003, भारत

PATIALA, 147003, INDIA



Date: As signed

(An ISO 9001, ISO 14001, ISO 45001 & ISO 50001, 5S & Green Building certified Organization)

No. PLW/M/ECS/Tech/Kavach

(Through Mail)

Sr. Div. Electrical Engineer, Electric Loco Shed, Saiyedpur Bhitri.

Email: elssyh123@gmail.com

Sub:- Fitment of KAVACH in three Phase Electric Loco. No. 42043 WAG9-HC.

Ref:- (i). Director General Stds./Electrical/RDSO letter no. EL/0.1.3/3 dated 21.08.2023.

(ii).Director General Stds./Electrical/RDSO letter no. EL/0.1.3/3 dated 26.09.2023

In ref. to the above letter's Loco No. 42043 has been dispatched with fittings for implementation of KAVACH system in locomotive at home shed in Zonal Railway. This Loco was dispatched to ELS/BSL/CR on 06.07.2025. The details of fittings are attached as Annexure-A (pneumatic fittings), Annexure-B (Kavach equipment mounting Brackets) & Annexure-C (Wago with harnessed lay out).

This is for your information & necessary action please.

Digitally signed by NISHANT BANSIWAL Date: 2025.08.06

(निशांत बंसीवाल)

उप मुख्य विद्युत अभियंता/लोको

प्रतिलिपि:-

CEE/Loco & CEE/D&Q, CMM, CELE/CR:- for kind information please Dy CME/Design, Dy. CMM/Depot: for information & necessary action please AEE/LAS, AWM/LFS&ABS, AWM/ECS: for necessary action please


Loco No. 42043

SN	PL No.	Description of item	Qty.
	29163341	ISOLATING COCK 3/8" (FEMALE) LEGRIS TYPE WITH VENT	04 nos.
1		ISOLATING COCK 3/8" (FEMALE) LEGRIS TYPE WITHOUT VENT	02 nos.
		TEE UNION 3/8"X3/8"X3/8" BRASS FITTINGS	02 nos.
		MALE CONNECTORS 3/8" TUBE OD X 3/8" BSPT, BRASS FITTINGS	09 nos.
-		MALE CONNECTORS 1/2" TUBE OD X 1/2" BSPT, BRASS FITTINGS	06 nos.
		FEMALE CONNECTORS (NYLON TUBE) DIA 6 TUBE X 3/8" BSPP BRASS FITTINGS	01 no.
	29611994	MALE CONNECTOR (NYLON TUBE) DIA 6 TUBE X 3/8" BSPP BRASS FITTINGS	03 nos
		FEMALE TEE 3/8" BSPP – BRASS	06 nos
2		HEX PLUG -3/8" BSPT – BRASS	02 nos
		FEMALE TEE 1/2" BSPP – BRASS	04 nos
		HEX NIPPLE 3/8X3/8" BSPT – BRASS	04 nos
		RED HEX NIPPLE 3/8X1/2" BSPT - BRASS	02 nos
		HEX PLUG – 1/2" BSPT – BRASS	04 nos
		MALE ELBOW CONNECTORS 3/8" TUBE OD X 3/8) BSPT. BRASS FITTINGS	02 nos
3	29170114	Copper Tube OD 9.52mm (3/8") X 1.245 Mm W.T X 6 Mtr	1.2Mtr

AWMABSELFS

SSE/G/ABS

SN	PL No.	Description of item	Quantity
1.	29611945	Mounting bracket arrangement provided for RF Antenna on the roof top of both driver cabs.	04 nos.
2.		Mounting bracket arrangement provided for GPS/GSM Antenna on the roof top of both driver cabs.	02 nos.
3.	, ;\$	Protection Guards for RFID reader provided behind the cattle guards of both side.	04 nos.
4.		Inspection door with latch provided on the both driver desk covers (LP side) in each cab to access isolation cock.	02 nos.
5.		Cable Entry Plate fitted for routing of cable with RF Antenna & GPS/GSM Antenna bracket.	06 nos.
6.		WAGO bracket fitted in Machine room at back side of SB-1.	01 no.
7.	-	One circular hole of 80 mm dia. provided in each cabs on LP side behind the driver desk toward the wall for routing of OCIP (DMI) cables.	02 nos
8.	-	80 mm holes provided on TM1 and TM6 Junction box inspection cover hole for drawing of RFID reader cables.	02 nos.
9.		DIN Rail fitted inside the driver desk (LP Side)	02 nos.





Annexure-C

SN	PL No.	Description of item	Quantity
1.	42310301	Flexible conduit size 25mm ² provided for RF-1, 2 & GPS Antenna cable layout from CAB-1&2 to Machine room.	06 mtr.
2.	29611982	Wago terminals in CAB-1&2 (25 nos. in each CAB).	50 nos.
3.	29611982	Wago terminal in Machine room at back side of SB-1.	75 nos.
4.	-	Harness provided from KAVACH SB to SB-1	07 wires
5.		Harness provided from KAVACH SB to SB-2	05 wires
6.	_	Harness provided from KAVACH SB to Pneumatic Panel	12 wires
7.	-	Harness provided from KAVACH SB to CAB-1	24 wires
8.	-	Harness provided from KAVACH SB to CAB-2	16 wires

AWMES

SSEIGIECS